

To: T10 Technical Committee  
From: Rob Elliott, HP (elliott@hp.com)  
Date: 3 May 2007  
Subject: 06-026r0 SAM-4 TASK ABORTED status clarifications

**Revision history**

Revision 0 (3 May 2007) First revision

**Related documents**

sam4r09 - SCSI Architecture Model - 4 (SAM-4) revision 9

**Overview**

It is not clear whether TASK ABORTED status is sent when tasks are aborted by a LOGICAL UNIT RESET task management function.

SPC-4 says the TAS bit set to one means “tasks aborted by the actions of an I\_T nexus other than the I\_T nexus on which the command was received shall be terminated with a TASK ABORTED status.” That implies a LOGICAL UNIT RESET task management function does generate TASK ABORTED status.

- a) Argument in favor of returning TASK ABORTED status: Conditions that were detected by a device server on only one of its target ports are not likely to be known by initiator ports attached to different SCSI domains in which the other target ports are attached. This status provides them notification that another initiator port caused their tasks to be aborted.
- b) Argument opposed to returning TASK ABORTED status: the device server might not be able to fend off the reset while it doles out TASK ABORTED statuses for each queued command. It is difficult to defer handling of power loss or hard reset. It is more conceivable to defer a LOGICAL UNIT RESET, which might involve firmware processing. However, an application could be sending LOGICAL UNIT RESET because the device server appears hung; asking the device server to send more status values is unlikely to unhang it.

Numerous changes are proposed to the “Aborting tasks” section that should make the rules clearer and more comprehensive.

This revision proposes that SCSI device conditions that abort tasks (and the task management functions that cause them - LOGICAL UNIT RESET and I\_T NEXUS RESET) do NOT cause TASK ABORTED status - only commands and task management functions that abort tasks without not cause SCSI device conditions (like ABORT TASK, ABORT TASK SET, and CLEAR TASK SET).

**Suggested changes to SAM-4**

**5.6.1 Status codes**

...

**TASK ABORTED.** This status shall be returned when a task is aborted by ~~another SCSI initiator port~~ by a command or task management function that does not cause a SCSI device condition (see 6.3) on another I\_T nexus and the Control mode page TAS bit is set to one (see 5.6.3).

...

**5.6 Aborting tasks**

~~**5.6.1 Mechanisms that cause tasks to be aborted**~~

A task is aborted when an ~~event or SCSI initiator device action~~ SCSI device condition (see 6.3), command, or task management function causes termination of the task prior to its ~~successful~~ completion by the device server.

~~The following events cause a task or several tasks to be aborted are capable of aborting tasks:~~

- ~~a) The return of an Execute Command service response of SERVICE DELIVERY OR TARGET FAILURE as described in 5.1;~~
- ~~b) A power on condition (see 6.3.1);~~

- c) A hard reset (see 6.3.2);
- d) A logical unit reset (see 6.3.3);
- e) An I\_T nexus loss (see 6.3.4);
- f) A power loss expected (see 6.3.5); or
- g) SCSI transport protocol specific conditions.

---

Editor's Note 1: resorted above list starting with power on and ending with power loss expected

---

An action command or task management function transmitted via one I\_T nexus may abort task(s) received on that I\_T nexus and/or task(s) received on other I\_T nexuses.

The following actions commands and task management functions affect only the task(s) received on the I\_T nexus on which the action command or task management function is transmitted:

- a) Completion of an ABORT TASK task management function directed to the specified task;
- b) Completion of an ABORT TASK SET task management function under the conditions specified in 7.3;
- c) Completion of an I\_T NEXUS RESET task management function; or
- d) Completion of a command with a CHECK CONDITION status, without establishing an ACA condition (see 5.8.1.3) or establishing an ACA condition (see 5.8.2.2), while the Control mode page (see SPC-3) contains fields that are set as follows:
  - A) The QERR field set to 01b and the TST field set to 001b; or
  - B) The QERR field set to 11b.

The actions shown in table 26 affect the task(s) received on the I\_T nexus on which the action is transmitted and/or task(s) received on other I\_T nexuses.

**Table 26— Actions that affect task(s) received on this or other I\_T nexuses**

<b>Action</b>	<b>Unit attention additional sense code, if any (see 5.6.3)</b>
Completion of a CLEAR TASK SET task management function referencing the task set containing the specified task	COMMANDS CLEARED BY ANOTHER INITIATOR
Completion of a command with a CHECK CONDITION status, with or without establishing an ACA condition, and the QERR field was set to 01b and the TST field was set to 000b in the Control mode page (see SPC-3)	COMMANDS CLEARED BY ANOTHER INITIATOR
Completion of a PERSISTENT RESERVE OUT command with a PREEMPT AND ABORT service action with a reservation key that is associated with the I_T nexus on which the task was received (see SPC-3)	COMMANDS CLEARED BY ANOTHER INITIATOR
Completion of a LOGICAL UNIT RESET task management function (see 7.7) directed to the logical unit	BUS DEVICE RESET FUNCTION OCCURRED
Receipt of a Power Loss Expected indication (see 6.3.5)	COMMANDS CLEARED BY POWER LOSS NOTIFICATION
SCSI transport protocol specific conditions	As defined by the applicable SCSI transport protocol standard

Table 27 lists the SCSI device conditions that cause tasks to be aborted, and for logical units defines the resulting unit attention condition additional sense code that is returned by the device server.

**Table 27 — SCSI device conditions that abort tasks**

<u>SCSI device condition</u>	<u>Scope</u>	<u>Unit attention condition (see 5.8.7) additional sense code, if any</u>	<u>Reference(s)</u>
<u>Power on</u>	<u>All tasks in the SCSI device</u>	<u>See table 33 in 6.2</u>	<u>6.3.1</u>
<u>Hard reset</u>	<u>Target device: All tasks in all logical units to which the SCSI port has access in the SCSI device</u>  <u>Initiator device: All tasks nexuses involving the SCSI port</u>		<u>6.3.2</u>
<u>Logical unit reset</u> <sup>a</sup>	<u>All tasks in the logical unit</u>		<u>6.3.3 and 7.7</u>
<u>L T nexus loss</u> <sup>a</sup>	<u>In each logical unit to which the SCSI port has access, all tasks with an L T nexus involving the SCSI port</u>		<u>6.3.4 and 7.6</u>
<u>Power loss expected</u>	<u>All tasks in the SCSI device</u>		<u>6.3.5</u>
<u>SCSI transport protocol specific conditions</u>	<u>As defined by the applicable SCSI transport protocol standard</u>		
<sup>a</sup> <u>This SCSI device condition is able to be invoked by a task management function listed in table 28.</u>			

[Table 28 lists the task management functions that cause tasks to be aborted, and for logical units defines the resulting unit attention condition additional sense code that is returned by a device server.](#)

**Table 28 — Task management functions that abort tasks**

<u>Task management function</u>	<u>Scope</u>	<u>Unit attention condition (see 5.8.7) additional sense code, if any</u>	<u>Reference(s)</u>
<a href="#">ABORT TASK</a>	<a href="#">Specified task</a>	None	<a href="#">7.2</a>
<a href="#">ABORT TASK SET</a>	<a href="#">All tasks in the task set with the same I T nexus</a>	None	<a href="#">7.3</a>
<a href="#">CLEAR TASK SET</a>	<a href="#">All tasks in the task set</a>	<a href="#">COMMANDS CLEARED BY ANOTHER INITIATOR</a>	<a href="#">7.5</a>
<a href="#">LOGICAL UNIT RESET</a>	<a href="#">See table 27 description of the logical unit reset condition</a>		
<a href="#">I T NEXUS RESET</a>	<a href="#">See table 27 description of the I T nexus loss condition</a>		

Table 29 lists the commands that cause tasks to be aborted, and for logical units defines the resulting unit attention condition additional sense code that is returned by a device server.

**Table 29 — Commands that abort tasks**

<u>Command</u>	<u>Scope</u>	<u>Unit attention condition (see 5.8.7) additional sense code, if any</u>	<u>Reference(s)</u>
Completion of a command with a CHECK CONDITION status if: a) the QERR field is set to 01b; and b) the TST field is set to 000b (i.e., shared) in the Control mode page (see SPC-4)	<u>All tasks in the task set</u>	<u>COMMANDS CLEARED BY ANOTHER INITIATOR</u>	<u>5.8.1.3 and 5.8.2.2</u>
Completion of a command with a CHECK CONDITION status if: a) the QERR field is set to 01b; and b) the TST field is set to 001b (i.e., per-I T nexus) in the Control mode page (see SPC-4)	<u>All tasks in the task set</u>	<u>None</u>	<u>5.8.1.3 and 5.8.2.2</u>
Completion of a command with a CHECK CONDITION status if the QERR field is set to 11b in the Control mode page (see SPC-4)	<u>All tasks in the task set with the same I T nexus as the command that was terminated</u>	<u>None</u>	<u>5.8.1.3 and 5.8.2.2</u>
Processing of a PERSISTENT RESERVE OUT command with a PREEMPT AND ABORT service action with a reservation key that is associated with the I T nexus on which the task was received (see SPC-4)	<u>All tasks from all I T nexuses with the specified reservation key</u>	<u>COMMANDS CLEARED BY ANOTHER INITIATOR</u>	<u>SPC-4</u>
The return of an Execute Command service response of SERVICE DELIVERY OR TARGET FAILURE as described in 5.1	<u>The indicated task</u>	<u>None</u>	
<u>Termination of an overlapped command</u>	<u>All tasks with the same I T nexus as the command that was terminated</u>	<u>None</u>	<u>5.8.3</u>

If one or more tasks are cleared or aborted, the affected tasks are also cleared from the initiator ports in a manner that is outside the scope of this standard.

#### **5.6.2 When a SCSI initiator port aborts tasks received on its own I\_T nexus**

~~When a SCSI initiator port causes task(s) received on its own I\_T nexus to be aborted, no notification that the task(s) have been aborted shall be returned to the SCSI initiator port~~ When a device server receives a command or task management function on an I T nexus that causes tasks on the same I T nexus to be aborted, it shall not return any notification that the those tasks have been aborted other than:

- a) the completion response for the command or task management function action that caused the task(s) to be aborted; and
- b) notification(s) associated with related effects of the action (e.g., a reset unit attention condition).

#### **5.6.3 When a SCSI initiator port aborts tasks received on other I\_T nexuses**

~~When a SCSI initiator port causes task(s) received on other I\_T nexus(es) to be aborted, the SCSI initiator port associated with every other I\_T nexus shall be notified that the task(s) have been aborted. The method of notification shall depend on the setting of the TAS bit in the Control mode page (see SPC-3) that applies to the SCSI initiator port(s) associated with the other I\_T nexus(es).~~

~~If the TAS bit is set to zero, the method of notification shall be a unit attention condition. The additional sense code for the unit attention condition depends on the action that caused the task(s) to be aborted as described in table 26 (see 5.6.1).~~

~~If the TAS bit is set to one, the method of notification shall be the termination of each aborted task with a TASK ABORTED status. A unit attention condition containing an additional sense code whose ADDITIONAL SENSE CODE field contains 2Fh (e.g., COMMANDS CLEARED BY ANOTHER INITIATOR, or COMMANDS CLEARED BY POWER LOSS NOTIFICATION), shall not be established. The establishment of any other applicable unit attention condition shall not be affected.~~

When a device server receives a command or task management function that does not cause a SCSI device condition on an I\_T nexus that causes tasks on other I\_T nexuses to be aborted, it shall return notifications for those tasks based on the setting of the TAS bit in the Control mode page (see SPC-3):

- a) If the TAS bit is set to zero, the device server:
  - A) shall not return status for the tasks that were aborted; and
  - B) shall establish a unit attention condition for the SCSI initiator port associated with each I\_T nexus containing tasks that were aborted with an additional sense code set as defined in table 27;
- b) If the TAS bit is set to one, the device server:
  - A) shall return TASK ABORTED status for each aborted task; and
  - B) shall not establish a unit attention condition for this reason.

When a logical unit is aborting one or more tasks received on an I\_T nexus using the TASK ABORTED status it should complete all of those tasks before entering additional tasks received on that I\_T nexus into the task set.

## 5.8 Command processing considerations and exception conditions

### 5.8.7 Unit Attention condition

Each logical unit shall generate a unit attention condition whenever one of the following events occurs:

- c) A power on (see 6.3.1), hard reset (see 6.3.2), logical unit reset (see 6.3.3), I\_T nexus loss (see 6.3.4), or power loss expected (see 6.3.5) occurs;
- d) A removable medium may have been changed;
- e) The mode parameters associated with this I\_T nexus have been changed by a task received on another I\_T nexus (i.e., initiator ports share mode parameters, see SPC-3);
- f) The log parameters associated with this I\_T nexus have been changed by a task received on another I\_T nexus (i.e., initiator ports share log parameters, see SPC-3);
- g) The version or level of microcode has been changed (see SPC-3);
- h) Tasks received on this I\_T nexus have been cleared by a task or a task management function associated with another I\_T nexus and the TAS bit was set to zero in the Control mode page associated with this I\_T nexus (see 5.6SPC-3);
- i) INQUIRY data has been changed (see SPC-3);
- j) The logical unit inventory has been changed (see SPC-3);
- k) The mode parameters in effect for the associated I\_T nexus have been restored from non-volatile memory (see SPC-3); or
- l) Any other event requiring the attention of the SCSI initiator device.

...

## 7.2 ABORT TASK

Request:

Service Response = ABORT TASK (IN ( I\_T\_L\_Q Nexus ))

Description:

This function shall be supported by all logical units.

The task manager shall abort the specified task, if any, as described in 5.6-2. Previously established conditions, including MODE SELECT parameters, reservations, and ACA shall not be changed by the ABORT TASK function.

A response of FUNCTION COMPLETE shall indicate that the task was aborted or was not in the task set. In either case, the SCSI target device shall guarantee that no further requests or responses are sent from the task.

All SCSI transport protocol standards shall support the ABORT TASK task management function.

### 7.3 ABORT TASK SET

Request:

Service Response = ABORT TASK SET (IN ( I\_T\_L Nexus ))

Description:

This function shall be supported by all logical units.

The task manager shall abort all tasks in the task set that were received on the specified I\_T nexus as described in 5.6. Tasks received on other I\_T nexuses or in other task sets shall not be aborted. This task management function performed is equivalent to a series of ABORT TASK requests.

Other previously established conditions, including MODE SELECT parameters, reservations, and ACA shall not be changed by the ABORT TASK SET function.

All SCSI transport protocol standards shall support the ABORT TASK SET task management function.

### 7.4 CLEAR ACA

Request:

Service Response = CLEAR ACA (IN ( I\_T\_L Nexus ))

Description:

This function shall be supported by a logical unit if it supports ACA (see 5.2).

For the CLEAR ACA task management function, the task set shall be the one defined by the TST field in the Control mode page (see SPC-3).

An application client requests a CLEAR ACA using the faulted I\_T nexus (see 3.1.39) to clear an ACA condition from the task set serviced by the logical unit. The state of all tasks in the task set shall be modified as described in 8.8. For a task with the ACA attribute (see 8.6.5) receipt of a CLEAR ACA function shall have the same effect as receipt of an ABORT TASK function (see 7.2) specifying that task. If successful, this function shall be terminated with a service response of FUNCTION COMPLETE.

If the task manager clears the ACA condition, any task within that task set may be completed subject to the requirements for task set management specified in clause 8.

The service response for a CLEAR ACA request received from an I\_T nexus other than the faulted I\_T nexus shall be FUNCTION REJECTED.

All SCSI transport protocol standards shall support the CLEAR ACA task management function.

### 7.5 CLEAR TASK SET

Request:

Service Response = CLEAR TASK SET (IN ( I\_T\_L Nexus ))

Description:

This function shall be supported by [all](#) logical units.

For the CLEAR TASK SET task management function, the task set shall be the one defined by the TST field in the Control mode page (see SPC-3). [If the TST field is set to 001b \(i.e., per-I\\_T nexus\), then CLEAR TASK SET is equivalent to ABORT TASK SET \(see 7.2\).](#)

~~All tasks in the task set shall be aborted~~[The task manager shall abort all tasks in the task set](#) as described in 5.6.

All pending status and sense data for the task set shall be cleared. Other previously established conditions, including MODE SELECT parameters, reservations, and ACA shall not be changed by the CLEAR TASK SET function.

All SCSI transport protocol standards shall support the CLEAR TASK SET task management function.

### 7.6 I\_T NEXUS RESET

Request:

Service Response = I\_T NEXUS RESET (IN ( I\_T\_L Nexus ))

Description:

SCSI transport protocols may or may not support I\_T NEXUS RESET and may or may not require logical units accessible through SCSI target ports using such transport protocols to support I\_T NEXUS RESET.

Each logical unit accessible through the SCSI target port shall perform the I\_T nexus loss functions specified in 6.3.4 for the I\_T nexus on which the function request was received, then the SCSI target device shall return a FUNCTION COMPLETE response. After returning a FUNCTION COMPLETE response, the logical unit(s) and the SCSI target port shall perform any additional functions specified by the SCSI transport protocol.

### 7.7 LOGICAL UNIT RESET

Request:

Service Response = LOGICAL UNIT RESET (IN ( I\_T\_L Nexus ))

Description:

This function shall be supported by all logical units.

Before returning a FUNCTION COMPLETE response, the logical unit shall perform the logical unit reset functions specified in 6.3.3.

NOTE 11 - Previous versions of this standard only required LOGICAL UNIT RESET support in logical units that supported hierarchical logical units.

All SCSI transport protocol standards shall support the LOGICAL UNIT RESET task management function.