

To: T10 Technical Committee  
 From: Dennis Spicher ([dennis.spicher@hp.com](mailto:dennis.spicher@hp.com)) and Rob Elliott, HP ([elliott@hp.com](mailto:elliott@hp.com))  
 Date: 20 May 2002  
 Subject: T10/02-189r0 SES-2 SPC-3 vendor-specific diagnostic pages

**Revision History**

Revision 0 (20 May 2002) first revision

**Related Documents**

ses-r08b - SCSI Enclosure Services revision 8b  
 spc3r06 - SCSI Primary Commands - 3 revision 6

**Overview**

Section 6.1 Diagnostic parameters and Table 2 – Diagnostic page codes for enclosure service devices of the SES specification define page codes 01h–0Fh as reserved for SES pages. In addition, page codes 80h–FFh are defined as vendor-specific pages for the non-enclosure services devices supporting access to an enclosure services process. This means that vendor-specific pages cannot be defined for the enclosure services device.

While the String In and String Out pages do provide a form of vendor specific SES page, mutual exclusion between multiple initiators becomes a problem. A String Out page needs to be defined to select the vendor-specific information to be presented in the String In page; this is a two step process that provides the opportunity for one application client to interfere with another application client.

Dedicated vendor-specific pages for the SES device will work much better.

**Suggested Changes**

Dedicate sixteen page codes from 10h–1Fh for use by enclosure services devices as vendor-specific.

Also, move all the SES-specific page names to an annex in SPC-3 rather than list them in section 8. SES defines its page ranges.

**SPC-3 8.1.1 Diagnostic page format and page codes for all device types**

...

**Table 167 - Diagnostic page codes**

Page Code	Diagnostic Page Name	Reference
00h	Supported Diagnostics Pages	8.1.2
<del>01h</del>	<del>Configuration</del>	<del>SES</del>
<del>02h</del>	<del>Enclosure Status/Control</del>	<del>SES</del>
<del>03h</del>	<del>Help Text</del>	<del>SES</del>
<del>04h</del>	<del>String In/Out</del>	<del>SES</del>
<del>05h</del>	<del>Threshold In/Out</del>	<del>SES</del>
<del>06h</del>	<del>Array Status/Control</del>	<del>SES</del>
<del>07h</del>	<del>Element Descriptor</del>	<del>SES</del>
<del>08h</del>	<del>Short Enclosure Status</del>	<del>SES</del>
<del>09h–0Fh</del>	<del>Reserved for SES</del>	<del>SES</del>
<del>01h - 1Fh</del>	<del>See SES-2</del>	<del>SES-2</del>
10h-20h - 3Fh	Pages that apply to all device types	
40h - 7Fh	See specific device type for definition	
80h	Vendor specific	

**Annex B Numeric order codes**

**B.x Diagnostic page codes**

Table B.n is a numerical order listing of the diagnostic page codes.

<b>Table B.n — Diagnostic Page Codes</b>		
<b>00h</b>	<b>D T L P W R S O M C A E B K</b>	<b>Supported Diagnostics Pages 8.1.2</b>
<b>01h</b>	<b>E</b>	<b>Configuration</b>
<b>02h</b>	<b>E</b>	<b>Enclosure Status/Control</b>
<b>03h</b>	<b>E</b>	<b>Help Text</b>
<b>04h</b>	<b>E</b>	<b>String In/Out</b>
<b>05h</b>	<b>E</b>	<b>Threshold In/Out</b>
<b>06h</b>	<b>E</b>	<b>Array Status/Control</b>
<b>07h</b>	<b>E</b>	<b>Element Descriptor</b>
<b>08h</b>	<b>E</b>	<b>Short Enclosure Status</b>
<b>09h - 0Fh</b>	<b>E</b>	<b>Reserved for SES</b>
<b>10h - 1Fh</b>	<b>E</b>	<b>Vendor-specific SES</b>
<b>20h - 3Fh</b>	<b>D T L P W R S O M C A E B K</b>	<b>Pages that apply to all device types</b>
<b>40h</b>		<b>See specific device type for definition</b>
<b>80h</b>		<b>Vendor specific</b>

### 6.1 Diagnostic parameters

This clause describes the diagnostic page structure and the diagnostic pages that are applicable to enclosure services devices and other device types that provide communications access to an enclosure services process. Each diagnostic page provides either control (outbound) or status (inbound) data transmission to or from the enclosure process.

The diagnostic page format is specified in [ANSI X3.304 SPC-3](#). All diagnostic pages have the diagnostic page header defined in [ANSI X3.304 SPC-3](#), including the PAGE CODE and PAGE LENGTH fields. The PAGE CODE field identifies the enclosure services page being sent or requested.

The page codes are defined in table 2.

**Table 2. Diagnostic page codes for enclosure services devices**

Page code	Description	Control or Status	Reference
00h	Supported diagnostics	Status	<a href="#">ANSI X3.304 SPC-3</a>
01h	Configuration	Status	6.1.1
02h	Enclosure Control	Control	6.1.2
02h	Enclosure Status	Status	6.1.3
03h	Help Text	Status	6.1.4
04h	String Out	Control	6.1.5
04h	String In	Status	6.1.6
05h	Threshold Out	Control	6.1.7
05h	Threshold In	Status	6.1.8
06h	Array Control	Control	6.1.9
06h	Array Status	Status	6.1.10
07h	Element Descriptor	Status	6.1.11
08h	Short Enclosure Status	Status	6.1.12
09h-0Fh	Reserved for SES	N/A	6.1
<a href="#">10h-1Fh</a>	<a href="#">Vendor-specific SES pages</a>	<a href="#">N/A</a>	<a href="#">6.1</a>
<del>10h</del> <a href="#">20h-3Fh</a>	Reserved (applies to all device type pages)	N/A	<a href="#">ANSI X3.304 SPC-3</a>
40h-7Fh	See specific device type for definition	N/A	<a href="#">ANSI X3.304 SPC-3</a>
80h-FFh	Vendor-specific pages	N/A	<a href="#">ANSI X3.304 SPC-3</a>

The supported page list specified in [ANSI X3.304 SPC-3](#) shall contain a list of all diagnostic page codes implemented by the device server in ascending order beginning with PAGE CODE 00h. If the device is capable of accessing a diagnostic function or enclosure function that may temporarily or

permanently be unavailable to the device, the PAGE CODE associated with that information shall be included in the list. The unavailability of the resources necessary to transfer a page shall not result in an error until a diagnostic command that requests the transfer of an enclosure service page is executed. The pages 09h-0Fh are reserved for future SES standardization. Non-enclosure services devices supporting access to an enclosure services process (see 4.1.2) shall direct pages 10h-1Fh to the enclosure services device and ~~may~~ shall include pages 00h-0Fh-1Fh in the supported page list.