

To: T10 Technical Committee  
From: Steve Johnson, LSI Logic (sjohnson@lsil.com)  
Date: 9 July, 2005  
Subject: 05-108r0 SAT-Task Management

**Revision history**

Revision 0 (9 July 2005) First revision

**Related documents**

satr04 - SCSI/ATA Translations 1.0 revision 4

**Overview**

Add support for ATA Queued feature set, Informative bus resets, QUERY TASK, and address editors notes for task management section.

**Suggested changes**

See text changes below.

## 1 Task Management Model

### 1.1 Overview

SAT implementations may support the full task management model or the basic task management model as defined by SAM-3 (~~see~~), depending on whether the SATL makes use of SATA native command queueing (NCQ), ATA queued feature set (TCQ), ~~and and/or~~ the tagged task management capabilities of the SATL itself. Elements of the task management model (e.g. SIMPLE task attribute and ORDERED task attribute) may be provided through the use of SATA NCQ, ATA TCQ, and/or queueing within the SATL itself, ~~or a combination thereof.~~

### 1.2 Queued commands

#### 1.2.1 Overview

SCSI provides for various modes of command queueing via task tags and ORDERED, SIMPLE, HEAD OF QUEUE, and ACA task attributes. SCSI devices do not report the maximum number of commands that may be queued, but report a status of BUSY or TASK SET FULL when a command is received and the ~~queue has no space~~ SATL does not have enough resources to process another command. ~~SATA NCQ supports up to 32 commands at a time.~~ The SATL has the option of mapping SCSI queued commands ~~directly to SATA native-queued commands~~ NCQ, TCQ and/or queueing commands internally.

#### 1.2.2 Mapping of SCSI ~~queued-tagged~~ commands to SATA ~~native-queued commands~~ NCQ and ATA TCQ

A SATL that forwards SCSI tagged commands to ~~a SATA an ATA~~ device using NCQ SATA NCQ or ATA TCQ, whether or not the SATL also queues commands internally, should either:

- a) report support for the basic task management model in SCSI standard INQUIRY data (BQue bit is 1 and CmdQue bit is 0), and follow the rules for the basic SCSI command queueing model (see SAM-3); or
- b) report support for the full task management model in SCSI standard INQUIRY data (BQue bit is 0 and CmdQue bit is 1), and report a value of 01b in the Queue error management (QErr) field of SCSI standard INQUIRY data.

A SATL that uses SATA NCQ or ATA TCQ may report support for the full task management model with a QERR field other than 01b only if the SATL reissues all queued commands aborted by the SATA-ATA device due to an error condition reported by the SATA-ATA device on any one of the queued commands.

---

Editor's Note 1: Is there a problem if data has already been transferred for an outstanding command that was aborted by the SATA device due to an error in another command?.....  
~~[SteveJ] data is not valid until status for the command is returned not matter if it has been transferred or not. I see no issues.~~

---

For each queued SCSI command the SATL forwards to ~~a SATA an ATA~~ device using NCQ SATA NCQ or ATA TCQ, the SATL shall allocate an inactive NCQ tag value (~~for NCQ~~, corresponding to an available bit in the reserved field of the Set Device Bits FIS). The SATL shall maintain a mapping between allocated NCQ or TCQ tags and the corresponding SCSI task tags.

The SATL shall detect the maximum queue depth supported by attached SATA devices (word 75 in IDENTIFY DEVICE), and ~~shall may~~ return TASK SET FULL STATUS in response to a SCSI command issued to the corresponding emulated SCSI device when the SATA device represented has the maximum number of queued commands outstanding; or the SATL may queue the command internally and return TASK SET FULL STATUS when the SATL exhausts it's internal queueing resources.

~~The mapping of NCQ tags to SCSI task tags may involve mapping more than one NCQ tag to a single SCSI task tag, for example, in cases where processing of a SCSI command involves processing of multiple ATA commands by the attached non-packet device.~~

---



---

Editor's Note 2: May want to add text to address how to handle sending ATA commands that cannot be queued when the SATA device has queued commands outstanding (i.e. have to wait for queued commands to complete before issuing the non-NCQ command). Does this impose an implicit requirement that the SATL queue commands (at least one anyway) internally? [\[SteveJ\] The SATL may return TASK SET FULL or BUSY. This is addressed below](#)

---



---

### 1.2.3 Commands the SATL queues internally

~~The SATL may only use SATA NCQ for READ and WRITE commands. Other new commands require~~ When queued commands are outstanding to the ATA device and new commands are received by the SATL that cannot be queued by the ATA device, the SATL shall queue the commands internally, or report a TASK SET FULL or BUSY condition to avoid receiving more commands until the non-READ or WRITE command is complete. Furthermore, if the SATL has outstanding READ or WRITE commands in process under NCQ, the SATL shall defer processing of the newly received non-READ or WRITE type command-queued commands until the queued commands complete processing. The SATL shall perform task management in accordance with the reported task management model supported in accordance with the requirements in SAM-3.

If the SATL supports queued commands and the translation requires a mix of queued and non-queued commands, the SATL shall defer processing of commands, complete processing of all outstanding queued commands, process the non-queued command, then continue processing the previously deferred commands.

### 1.2.4 Multi-initiator and multi-port command queuing

If the SATL is accessed through a SCSI target port the SATL may be accessible by more than one initiator port and through more than one SCSI target port. As specified in SAM-3, the task tags maintained in the SATL mapping of task tags to NCQ tags or TCQ tags shall be qualified by the initiator ID and port ID from which the command was received. When translating from an NCQ tag or TCQ tag to the corresponding SCSI task tag, the SATL shall determine the correct SCSI port and initiator using the qualification information associated with the SCSI task tag. The SATL may report TASK SET FULL even if the SATA device has available NCQ tags or TCQ tags in order to maintain tags available for other initiators.

## 1.3 Task Management Functions

This section describes the translation of SCSI task management functions to ATA or SATA equivalents.

NOTE 1 - Due to architectural differences, not all task management functions can be successfully translated to ATA commands or control operations.

### 1.3.1 ABORT TASK

The SATL may process the ABORT TASK service request in any of the following ways:

- a) If no commands have yet been issued to the non-packet device for the processing of the specified SCSI task tag the SATL shall delete the specified task from the SATL internal context and respond to the ABORT TASK request with FUNCTION COMPLETE.
- b) If the only command(s) being processed in the non-packet device are related to the SCSI task specified by the ABORT TASK request, then the SATL may abort the SATA command(s) (e.g. by issuing a NOP), and respond with FUNCTION COMPLETE.
- c) If the non-packet device is processing one or more commands related to the SCSI task specified by the ABORT TASK request, and is also processing at least one other command related to a different SCSI task, and the SATL reports the full task management model and a QErr bit value other than 01b, then the SATL shall abort the command in a manner that does not prevent the processing of other commands being processed by the attached non-packet device, and shall return FUNCTION COMPLETE status.

NOTE 2 - It may be that the first place the SATL can abort the command without preventing the processing of other commands is when the attached non-packet device returns completion status for the ATA command. In this case the SATL would not provide a SCSI response for the aborted command, even though processing completed in the ATA domain, but instead return FUNCTION COMPLETE for the ABORT TASK request.

- d) If the SATL reports support of the basic task management model, or reports support for the full task management model and a QErr field value of 01b, then the SATL may abort outstanding ATA commands (e.g. by issuing a NOP), and shall respond to the ABORT TASK request with FUNCTION COMPLETE. The SATL shall return TASK ABORTED status for other SCSI tasks terminated because the corresponding ATA commands were aborted along with the one specified in the ABORT TASK request.

---



---

Editor's Note 3: Are there other conditions besides QErr that affect the behavior here?

---



---

- e) If the SATL cannot abort the requested command, it shall respond to the ABORT TASK request with SERVICE DELIVERY ~~OR~~or TARGET FAILURE.

---



---

Editor's Note 4: Still need to specify non-packet device state after processing (e.g. restore configuration options,...)

---



---

### 1.3.2 ABORT TASK SET

The SATL may handle the ABORT TASK SET service request differently depending on whether the SATL provides multiple initiators access to the emulated SCSI device or not. If the SATL provides multiple initiator access to the emulated SCSI device, the SATL shall process the ABORT TASK SET service request as follows:

If the SATL does not provide multiple initiators access to the emulated SCSI device, the SATL shall process the service request as follows:

- a) If no commands have yet been issued to the non-packet device for the processing of the specified SCSI task tag the SATL shall delete all tasks in the task set from the SATL internal context and respond to the ABORT TASK SET request with FUNCTION complete.
- b) If the only command(s) being processed in the non-packet device are related to the SCSI tasks in the task set, then the SATL may abort the SATA command(s) (e.g. by issuing a NOP), and respond with FUNCTION complete.
- c) If the SATL reports support of the basic task management model, or reports support for the full task management model and a QErr field value of 01b, then the SATL may abort outstanding ATA commands (e.g. by issuing a NOP), and shall respond to the ABORT TASK SET request with FUNCTION complete.
- d) If the SATL cannot abort tasks in the task set, it shall respond to the service request with SERVICE DELIVERY OR TARGET FAILURE.

If the SATL provides multiple initiators access to the emulated SCSI device, the SATL shall process the service request as follows:

- a) If the SATL supports the basic task management model, the SATL may abort outstanding ATA commands (e.g. by issuing a NOP), and respond with FUNCTION complete.
- b) If the SATL supports the full task management model and reports a QErr value of 01b, the SATL may abort outstanding ATA commands (e.g. by issuing a NOP), and respond with FUNCTION complete.
- c) If the SATL supports the full task management model and reports a QErr value other than 01b, the SATL may either abort the outstanding ATA commands or not, and shall return SERVICE DELIVERY OR TARGET FAILURE in response to the CLEAR TASK SET service request.

### 1.3.3 CLEAR ACA

The SATL shall not support auto-contingent allegiance. The SATL shall indicate ACA is not supported by reporting a value of 0 in the NORMACA bit in standard INQUIRY data. The SATL shall respond to a CLEAR ACA service request with FUNCTION REJECTED.

### 1.3.4 CLEAR TASK SET

If the SATL reports support of the basic task management model or reports support of the full task management model with a QErr field value of 01b, the SATL shall reject the service request returning a status of FUNCTION REJECTED.

If the SATL reports support of the full task management model and a QErr value other than 01b, the SATL may either abort the outstanding ATA commands or not, and shall return SERVICE DELIVERY ~~OR~~ or TARGET FAILURE in response to the CLEAR TASK SET service request. The SATL may reset the device to clear any outstanding commands.

---



---

Editor's Note 5: Or perhaps the SATL should just reset the device? [SteveJ] addressed above.

---



---

### 1.3.5 LOGICAL UNIT RESET

LOGICAL UNIT RESET shall cause the SATL to issue a software reset (i.e., set the SRST bit to one in the Device Control register, then set the bit to zero) to the non-packet device representing the specified logical unit. Any persistent behaviors shall be reestablished by the SATL afterwards, including any behaviors related to saveable mode parameters.

NOTE 3 - BUS RESET is commonly used by SCSI application layers to hard reset each device mapped to a target id on a given SCSI bus. The SATL may translate the BUS RESET by performing a protocol specific HARD RESET to each target device (i.e. SATA COM RESET or SAS PHY HARD RESET).

---



---

Editor's Note 6: ATAPI may need special handling, but that issue is being deferred for now, and applies to all task management functions since ATAPI doesn't provide a standard way to send task management requests.

---



---

### 1.3.6 QUERY TASK

~~The SATL shall not support the QUERY TASK service request and shall return FUNCTION REJECTED to a QUERY TASK service request.~~

QUERY TASK shall cause the SATL to search for the specified task and if found, return a response of FUNCTION SUCCEEDED. If the specified task is not found the SATL shall return a response of FUNCTION COMPLETE.

---



---

Editor's Note 7: Suggestion - Query task shouldn't be prohibited. At least one SCSI transport, SAS, requires a target device to support QUERY TASK, and so if the SATL is behind a SAS target port, there would be conflicting requirements. [SteveJ] addressed above and changed to "shall"

---



---



---



---

Editor's Note 8: The original proposal included BUS RESET here. SAM-3 does not define "BUS RESET". This is a concept carried over from earlier SPI standards. The intent is to represent a HARD RESET condition, which is generated by transport-specific means. SAS and SATA already define the behavior of HARD RESET. BUS RESET should be addressed in an informative annex. The editor is awaiting a formal proposal to add informative text for handling BUS RESET. [SteveJ]

[addressed in note above.](#)

---

## 1.4 SCSI Control Byte

### 1.4.1 CONTROL byte overview

Every SCSI CDB contains a CONTROL byte (see SAM-3). Table 1 describes SATL handling of the CONTROL byte.

**Table 1 — Control byte fields**

Field	SATType	Description or reference
VENDOR SPECIFIC(12h)		The SATL may use this field for vendor-specific purposes.
NACA	U	If set to one, the SATL shall return a CHECK CONDITION with the sense key set to ILLEGAL REQUEST and additional sense code set to INVALID FIELD IN CDB if a value of 1 is specified in this field.
LINK	U	If set to one, the SATL shall return a CHECK CONDITION with the sense key set to ILLEGAL REQUEST and additional sense code set to INVALID FIELD IN CDB if a value of 1 is specified in this field.