

To: T10 Technical Committee  
 From: Tyson Hartshorn, LSI Logic  
 Date: April 2, 2007  
 Subject: Serial Attached SCSI - 2 (SAS-2)

### **Revision history**

Revision 0, 07-102r0 (March 22, 2007) First revision.  
 Revision 1, 07-102r1 (April 2, 2007) Second revision.

### **Related documents**

sas2r09a - Serial Attached SCSI 2.

### **Overview**

The current method for retrieving phy event information is by per phy SMP requests. There is also no way of knowing that new phy event information is available. This proposal suggests a methods that both indicate when new phy event information is available and provide an optimized interface for retrieving this information.

### **Suggested changes**

Move SMP functions 14h-17h from phy based SMP group to phy descriptor list group in range 20h-2fh.

Add 16 bit fields to the REPORT GENERAL and DISCOVER LIST responses to indicate the index of the last self configuration status log written by the management device server.

Remove phy identifier field from the REPORT PHY EVENT INFORMATION request and instead provide a 16 bit field that indicates the index of the first phy event information descriptor to return.

Add 8 bit phy identifier field to the REPORT PHY EVENT INFORMATION descriptor to indicate which phy this information is for.

Add 3 16 bit fields in the REPORT PHY EVENT INFORMATION response to indicate the index of the first descriptor returned in the response, the total number of descriptors available, and the maximum descriptor index value.

**Table 180 — SMP functions (FUNCTION field) (part 1 of 3)**

<b>Code</b>	<b>SMP function</b>	<b>Description</b>	<b>Reference</b>
00h	REPORT GENERAL	Return general information about the device	10.4.3.3
01h	REPORT MANUFACTURER INFORMATION	Return vendor and product identification	10.4.3.4
02h	READ GPIO REGISTER	See SFF-8485	
03h	REPORT SELF-CONFIGURATION STATUS	Return status of the discover process in a self-configuring expander device	10.4.3.5
04h	REPORT ZONE PERMISSION	Return zone permission table active or shadow values	10.4.3.6
05h - 0Fh	Reserved for general SMP input functions		
10h	DISCOVER	Return information about the specified phy	10.4.3.7
11h	REPORT PHY ERROR LOG	Return error logging information about the specified phy	10.4.3.8

**Table 180 — SMP functions (FUNCTION field) (part 2 of 3)**

Code	SMP function	Description	Reference
12h	REPORT PHY SATA	Return information about a phy currently attached to a SATA phy	10.4.3.9
13h	REPORT ROUTE INFORMATION	Return phy-based expander route table information	10.4.3.10
14h - 1Fh	Reserved for phy-based SMP input functions		
<u>20h</u>	REPORT PHY EVENT INFORMATION	Return phy event information.. for the specified- phy	9.4.5.4
<u>21h</u>	<u>REPORT BROADCASTS</u>	Return Broadcast counts	10.4.3.12
<u>22h</u>	DISCOVER LIST	Return information about the specified phys	
<u>23h</u>	REPORT EXPANDER ROUTE TABLE	Return contents of the expander-based expander route table	10.4.3.14
<u>24h - 2Fh</u>	<u>Reserved for phy descriptor list SMP input functions</u>		
<del>20h</del> <u>30h-3Fh</u>	Reserved for SMP input functions		
40h - 7Fh	Vendor specific		
80h	CONFIGURE GENERAL	Configure the device	10.4.3.15
81h	ENABLE DISABLE ZONING	Enable or disable zoning	10.4.3.16
82h	WRITE GPIO REGISTER	See SFF-8485	
83h - 84h	Reserved for general SMP output functions		
85h	ZONED BROADCAST	Transmit the specified Broadcast on the expander ports in the specified zone group(s)	10.4.3.17
86h	ZONE LOCK	Lock a zoning expander device	10.4.3.18
87h	ZONE ACTIVATE	Set the zoning expander active values equal to the zoning expander shadow values	10.4.3.19
88h	ZONE UNLOCK	Unlock a zoning expander device	10.4.3.20
89h	Reserved for a zoning function		
8Ah	CONFIGURE ZONE PHY INFORMATION	Configure zone phy information	10.4.3.21
8Bh	CONFIGURE ZONE PERMISSION TABLE	Configure the zone permission table	10.4.3.22
8Ch - 8Fh	Reserved for general SMP output functions		
90h	CONFIGURE ROUTE INFORMATION	Change phy-based expander route table information	10.4.3.23
91h	PHY CONTROL	Request actions by the specified phy	10.4.3.24
92h	PHY TEST FUNCTION	Request a test function by the specified phy	10.4.3.25
93h	CONFIGURE PHY EVENT INFORMATION	Configure phy event information for the specified phy	10.4.3.26

**Table 180 — SMP functions (FUNCTION field) (part 3 of 3)**

Code	SMP function	Description	Reference
94h - 9Fh	Reserved for phy-based SMP output functions		
A0h - BFh	Reserved for SMP output functions		
C0h - FFh	Vendor specific		

**Table 181 — FUNCTION RESULT field (part 1 of 4)**

Code	Name	SMP function(s)	Description
00h	SMP FUNCTION ACCEPTED	All	The management device server supports the SMP function. The ADDITIONAL RESPONSE BYTES field contains the requested information.
01h	UNKNOWN SMP FUNCTION	Unknown	The management device server does not support the requested SMP function. The ADDITIONAL RESPONSE BYTES field may be present but shall be ignored.
02h	SMP FUNCTION FAILED	All	The management device server supports the SMP function, but the requested SMP function failed. The ADDITIONAL RESPONSE BYTES may be present but shall be ignored.
03h	INVALID REQUEST FRAME LENGTH	All	The management device server supports the SMP function, but the SMP request frame length was invalid (i.e., did not match the frame size defined for the function). The ADDITIONAL RESPONSE BYTES may be present but shall be ignored.
04h	INVALID EXPANDER CHANGE COUNT	CONFIGURE GENERAL, ENABLE DISABLE ZONING, ZONE LOCK, CONFIGURE ZONE PHY INFORMATION, CONFIGURE ZONE PERMISSION TABLE, CONFIGURE ROUTE INFORMATION, PHY CONTROL, PHY TEST FUNCTION, CONFIGURE PHY EVENT INFORMATION	The management device server supports the SMP function, but the EXPECTED EXPANDER CHANGE COUNT field does not match the current expander change count. The ADDITIONAL RESPONSE BYTES may be present but shall be ignored.
05h	BUSY	ZONE UNLOCK	The locked zoning expander device is processing the activate step.

**Table 181 — FUNCTION RESULT field (part 2 of 4)**

Code	Name	SMP function(s)	Description
06h	INCOMPLETE DESCRIPTOR LIST	ZONED BROADCAST, CONFIGURE ZONE PHY INFORMATION, CONFIGURE ZONE PERMISSION TABLE, CONFIGURE PHY EVENT INFORMATION	The request frame length results in the truncation of a multi-byte field or descriptor list (e.g., in the ZONED BROADCAST request, the request frame is not large enough to contain the number of broadcast source zone groups specified by the NUMBER OF BROADCAST SOURCE ZONE GROUPS field). The ADDITIONAL RESPONSE BYTES may be present but shall be ignored.
10h	PHY DOES NOT EXIST	DISCOVER, DISCOVER LIST, REPORT PHY ERROR LOG, REPORT PHY SATA, REPORT ROUTE INFORMATION, REPORT PHY EVENT INFORMATION, REPORT PHY BROADCAST COUNTS, CONFIGURE ZONE PHY INFORMATION, CONFIGURE ROUTE INFORMATION, PHY CONTROL, PHY TEST FUNCTION, CONFIGURE PHY EVENT INFORMATION	The phy specified by the PHY IDENTIFIER field or the STARTING PHY IDENTIFIER field in the SMP request frame does not exist (e.g., the value is not within the range of zero to the value of the NUMBER OF PHYs field reported in the SMP REPORT GENERAL response). The ADDITIONAL RESPONSE BYTES field may be present but shall be ignored.
11h	INDEX DOES NOT EXIST	REPORT ROUTE INFORMATION, CONFIGURE ROUTE INFORMATION	The phy specified by the PHY IDENTIFIER field in the SMP request frame does not have the table routing attribute (see 4.6.7.1), or the expander route index specified by the EXPANDER ROUTE INDEX field does not exist (i.e., the value is not in the range of 0000h to the value of the EXPANDER ROUTE INDEXES field in the SMP REPORT GENERAL response). The ADDITIONAL RESPONSE BYTES field may be present but shall be ignored.
12h	PHY DOES NOT SUPPORT SATA	REPORT PHY SATA and PHY CONTROL (TRANSMIT SATA PORT SELECTION SIGNAL)	The phy specified by the PHY IDENTIFIER field in the SMP request frame is not part of an STP target port. The ADDITIONAL RESPONSE BYTES field may be present but shall be ignored.
13h	UNKNOWN PHY OPERATION	PHY CONTROL	The operation specified by the PHY OPERATION field in the SMP request frame is unknown. The SMP function had no affect. The ADDITIONAL RESPONSE BYTES field may be present but shall be ignored.

Table 181 — FUNCTION RESULT field (part 3 of 4)

Code	Name	SMP function(s)	Description
14h	UNKNOWN PHY TEST FUNCTION	PHY TEST FUNCTION	The operation specified by the PHY TEST FUNCTION field in the SMP request frame is unknown. The ADDITIONAL RESPONSE BYTES field may be present but shall be ignored.
15h	PHY TEST FUNCTION IN PROGRESS	PHY TEST FUNCTION	The specified phy is already performing a phy test function. The ADDITIONAL RESPONSE BYTES field may be present but shall be ignored.
16h	PHY VACANT	DISCOVER, REPORT PHY ERROR LOG, REPORT PHY SATA, REPORT ROUTE INFORMATION, REPORT PHY EVENT INFORMATION, CONFIGURE ROUTE INFORMATION, PHY CONTROL, CONFIGURE PHY EVENT INFORMATION	The management device server processing the SMP request frame does not have access to the phy (e.g., because of zoning or vendor-specific reasons), although the value is within the range of zero to the value of the NUMBER OF PHYs field reported in the SMP REPORT GENERAL response. The ADDITIONAL RESPONSE BYTES field may be present but shall be ignored.
17h	UNKNOWN PHY EVENT INFORMATION SOURCE	CONFIGURE PHY EVENT INFORMATION	The phy event information source specified by a PHY EVENT INFORMATION SOURCE field is not supported. The ADDITIONAL RESPONSE BYTES may be present but shall be ignored.
18h	UNKNOWN DESCRIPTOR TYPE	DISCOVER LIST, <u>REPORT PHY EVENT INFORMATION.</u>	The descriptor type specified by the DESCRIPTOR TYPE field is not supported. The ADDITIONAL RESPONSE BYTES may be present but shall be ignored.
19h	UNKNOWN PHY FILTER	DISCOVER LIST	The phy filter specified by the PHY FILTER field is not supported. The ADDITIONAL RESPONSE BYTES may be present but shall be ignored.
1Ah	LOGICAL LINK RATE NOT SUPPORTED	PHY CONTROL	The logical link rate specified by the REQUESTED LOGICAL LINK RATE field is not supported.
20h	SMP ZONE VIOLATION	CONFIGURE GENERAL, ENABLE DISABLE ZONING, ZONED BROADCAST, PHY CONTROL, PHY TEST FUNCTION, CONFIGURE PHY EVENT INFORMATION	The management device server supports the function, but zoning is enabled and the SMP initiator port does not have access to a necessary zone group according to the zone permission table (see 4.9.3.2). The ADDITIONAL RESPONSE BYTES may be present but shall be ignored.

**Table 181 — FUNCTION RESULT field (part 4 of 4)**

Code	Name	SMP function(s)	Description
21h	NO MANAGEMENT ACCESS RIGHTS	ENABLE DISABLE ZONING, ZONE LOCK	<p>Either:</p> <ul style="list-style-type: none"> <li>a) the ZONE ENABLE bit is set to zero and a zoning expander device processes an ENABLE DISABLE ZONING request when the PHYSICAL PRESENCE bit is set to zero; or</li> <li>b) the ZONE ENABLE bit is set to one and a zoning expander device processes a ZONE LOCK request when the ZONE LOCK bit is set to zero, the PHYSICAL PRESENCE bit is set to zero, and the zone manager does not have access to zone group 2.</li> </ul> <p>The ADDITIONAL RESPONSE BYTES field may be present but shall be ignored.</p>
22h	UNKNOWN ENABLE DISABLE ZONING VALUE	ENABLE DISABLE ZONING	The ENABLE DISABLE ZONING field is set to 11b (i.e., Reserved). The ADDITIONAL RESPONSE BYTES field may be present but shall be ignored.
23h	ZONE LOCK VIOLATION	ENABLE DISABLE ZONING, ZONE LOCK, ZONE ACTIVATE, ZONE UNLOCK, CONFIGURE ZONE PHY INFORMATION, CONFIGURE ZONE PERMISSION TABLE	<p>The ZONE ENABLE bit is set to one and:</p> <ul style="list-style-type: none"> <li>a) an unlocked zoning expander device receives an SMP zone configuration function request, a ZONE ACTIVATE request, or a ZONE UNLOCK request from an SMP initiator port that is not the active zone manager; or</li> <li>b) a locked zoning expander device receives an SMP ZONE LOCK request, an SMP zone configuration function request, a ZONE ACTIVATE request, or a ZONE UNLOCK request from an SMP initiator port that is not the active zone manager.</li> </ul>
24h	NOT ACTIVATED	ZONE UNLOCK	The ACTIVATE REQUIRED bit in the request is set to one but the locked zoning expander device has not processed the activate step.
25h	UNKNOWN ZONE PHY INFORMATION VALUE	CONFIGURE ZONE PHY INFORMATION	A specified zone phy information value is not supported. The ADDITIONAL RESPONSE BYTES field may be present but shall be ignored.
All others	Reserved		

Table 182 defines the response format.

**Table 182 — REPORT GENERAL response (part 1 of 2)**

Byte\Bit	7	6	5	4	3	2	1	0
0	SMP FRAME TYPE (41h)							
1	FUNCTION (00h)							
2	FUNCTION RESULT							
3	RESPONSE LENGTH ( <del>0Eh</del> ) (0Fh)							
4	(MSB)	EXPANDER CHANGE COUNT						(LSB)
5								
6	(MSB)	EXPANDER ROUTE INDEXES						(LSB)
7								
8	Reserved							
9	NUMBER OF PHYS							
10	TABLE TO TABLE SUPPORTED	Reserved			CONFIGURES OTHERS	CONFIGURING	EXTERNALLY CONFIGURABLE ROUTE TABLE	
11	Reserved							
12	ENCLOSURE LOGICAL IDENTIFIER							
19								
20	Reserved							
29								
30	(MSB)	STP BUS INACTIVITY TIME LIMIT						(LSB)
31								
32	(MSB)	STP MAXIMUM CONNECT TIME LIMIT						(LSB)
33								
34	(MSB)	STP SMP I_T NEXUS LOSS TIME						(LSB)
35								
36	Reserved			ZONE LOCKED	PHYSICAL PRESENCE SUPPORTED	PHYSICAL PRESENCE ASSERTED	ZONING SUPPORTED	ZONING ENABLED
37	Reserved							
38	(MSB)	MAXIMUM NUMBER OF ROUTED SAS ADDRESSES						(LSB)
39								



Table 182 — REPORT GENERAL response (part 2 of 2)

Byte\Bit	7	6	5	4	3	2	1	0	
40	ACTIVE ZONE MANAGER SAS ADDRESS								
47									
48	(MSB)	ZONE LOCK INACTIVITY TIME LIMIT							
49								(LSB)	
50	Reserved								
51	Reserved								
52	Reserved								
53	FIRST ENCLOSURE CONNECTOR ELEMENT INDEX								
54	NUMBER OF ENCLOSURE CONNECTOR ELEMENT INDEXES								
55	Reserved								
56	REDUCED FUNCTIONALITY	Reserved							
57	TIME TO REDUCED FUNCTIONALITY								
58	INITIAL TIME TO REDUCED FUNCTIONALITY								
59	MAXIMUM REDUCED FUNCTIONALITY TIME								
<del>60</del>	(MSB)	<del>CRC</del>							
<del>63</del>								(LSB)	
60	Reserved								
61	Reserved								
<u>62</u>	(MSB)	<u>LAST PHY EVENT INFORMATION DESCRIPTOR INDEX</u>							
<u>63</u>								(LSB)	
<u>64</u>	(MSB)	<u>CRC</u>							
<u>67</u>								(LSB)	

The SMP FRAME TYPE field shall be set to 41h.

The FUNCTION field shall be set to 00h.

The FUNCTION RESULT field is defined in 10.4.3.2.

The RESPONSE LENGTH field shall be set to ~~0Eh~~ 0Fh. For compatibility with previous versions of this standard, a RESPONSE LENGTH field set to 00h indicates that there are 6 dwords before the CRC field.

The EXPANDER CHANGE COUNT field counts the number of Broadcast (Change)s originated by an expander device (see 7.11). Management device servers in expander devices shall support this field. management device servers in other device types (e.g., end devices) shall set this field to 0000h. This field shall be set to at least 0001h at power on. If the expander device has originated Broadcast (Change) for any reason described in 7.11 since transmitting a REPORT GENERAL response, it shall increment this field at least once from the

value in the previous REPORT GENERAL response. It shall not increment this field when forwarding a Broadcast (Change). This field shall wrap to at least 0001h after the maximum value (i.e., FFFFh) has been reached.

NOTE 81 - Application clients that use the EXPANDER CHANGE COUNT field should read it often enough to ensure that it does not increment a multiple of 65 536 times between reading the field.

NOTE 82 - Management device servers in expander devices compliant with previous versions of this standard may return an EXPANDER CHANGE COUNT field set to 0000h.

---

---

Editor's Note 61: A BROADCAST EXPANDER COUNT field is also needed, so recipients of that BROADCAST can pinpoint which expander it came from. Expander-wide counts for all BROADCASTs (e.g. reception of ASYNCHRONOUS EVENT) might be needed.

---

---

The EXPANDER ROUTE INDEXES field contains the maximum number of expander route indexes per phy for the expander device (see 4.6.7.3). Management device servers in externally configurable expander devices containing phy-based expander route tables shall support this field. Management device servers in other device types (e.g., end devices, externally configurable expander devices with expander-based expander route tables, and self-configuring expander devices) shall set the EXPANDER ROUTE INDEXES field to zero. Not all phys in an externally configurable expander device are required to support the maximum number indicated by this field.

The NUMBER OF PHYS field contains the number of phys in the device, including any virtual phys and any vacant phys.

A TABLE TO TABLE SUPPORTED bit set to one indicates the expander device is a self-configuring expander device that supports its table routing phys being attached to table routing phys in other expander devices. The TABLE TO TABLE SUPPORTED bit shall only be set to one if the EXTERNALLY CONFIGURABLE ROUTE TABLE bit is set to zero. A TABLE TO TABLE SUPPORTED bit set to zero indicates the expander device is not a self-configuring expander device that supports its table routing phys being attached to table routing phys in other expander devices.

A CONFIGURES OTHERS bit set to one indicates that the expander device is a self-configuring expander device that performs the configuration subprocess defined in 4.8. A CONFIGURES OTHERS bit set to zero indicates the expander device may or may not perform the configuration subprocess. Self-configuring expander devices compliant with this standard shall set the CONFIGURES OTHERS bit to one.

NOTE 83 - If the CONFIGURES OTHERS bit is set to zero, the expander device may configure all externally configurable expander devices in the SAS domain.

A CONFIGURING bit set to one indicates that either:

- a) the management device server is in a self-configuring expander device, the self-configuring expander device's management application client is currently performing the discover process (see 4.7), and it has identified at least one change to its expander routing table; or
- b) the zoning expander device is locked and the zoning expander shadow values differ from the zoning expander active values.

A CONFIGURING bit set to zero indicates that the management device server is not in a self-configuring expander device currently performing the discover process and changing its expander routing table. Changes in this bit from one to zero result in a Broadcast (Change) being originated (see 7.11). Management device servers in self-configuring expander devices shall support this bit. Management device servers in externally configurable expander devices and in other device types shall set the CONFIGURING bit to zero.

An EXTERNALLY CONFIGURABLE ROUTE TABLE bit set to one indicates that the management device server is in an externally configurable expander device that has a phy-based expander route table that is required to be configured with the SMP CONFIGURE ROUTE INFORMATION function (see 4.6.7.3). An EXTERNALLY CONFIGURABLE ROUTE TABLE bit set to zero indicates that the management device server is not in an externally

configurable expander device (e.g., it is in an end device, in a self-configuring expander device, or in an expander device with no phys with table routing attributes).

The ENCLOSURE LOGICAL IDENTIFIER field identifies the enclosure, if any, in which the device is located, and is defined in SES-2. The ENCLOSURE LOGICAL IDENTIFIER field shall be set to the same value reported by the enclosure services process, if any, for the enclosure. An ENCLOSURE LOGICAL IDENTIFIER field set to zero indicates no enclosure information is available.

The STP BUS INACTIVITY TIME LIMIT field contains the bus inactivity time limit for STP connections which is set by the CONFIGURE GENERAL function (see 10.4.3.15).

The STP MAXIMUM CONNECT TIME LIMIT field contains the maximum connect time limit for STP connections which is set by the CONFIGURE GENERAL function (see 10.4.3.15).

The STP SMP I\_T NEXUS LOSS TIME field contains the time that an STP target port and an SMP initiator port retry certain connection requests which is set by the CONFIGURE GENERAL function (see 10.4.3.15).

A ZONE LOCKED bit set to one indicates that the zoning expander device is locked (see 4.9.6.2). A ZONE LOCKED bit set to zero indicates that the zoning expander device is not locked.

A PHYSICAL PRESENCE SUPPORTED bit set to one indicates that the expander device supports physical presence as a mechanism for allowing zoning to be enabled or disabled from phys in zone groups without access to zone group 2. A PHYSICAL PRESENCE SUPPORTED bit set to zero indicates that the expander device does not support physical presence as a mechanism for allowing zoning to be enabled or disabled.

A PHYSICAL PRESENCE ASSERTED bit set to one indicates that the expander device is currently detecting physical presence. A PHYSICAL PRESENCE ASSERTED bit set to zero indicates that the expander device is not currently detecting physical presence. The PHYSICAL PRESENCE ASSERTED bit shall be set to zero if the PHYSICAL PRESENCE SUPPORTED bit is set to zero.

A ZONING SUPPORTED bit set to one indicates that zoning is supported by the expander device (i.e., it is a zoning expander device). A ZONING SUPPORTED bit set to zero indicates that zoning is not supported by the expander device.

A ZONING ENABLED bit set to one indicates that zoning is enabled in the expander device. A ZONING ENABLED bit set to zero indicates that zoning is disabled in the expander device. The ZONING ENABLED bit shall be set to zero if the ZONING SUPPORTED bit is set to zero.

The MAXIMUM NUMBER OF ROUTED SAS ADDRESSES field contains the number of routed SAS addresses in an expander-based expander route table (see 4.6.7.3 and 4.9.3.4). Management device servers in expander devices containing expander-based expander route tables shall support this field. Management device servers in other device types (e.g., end devices and expander devices with phy-based expander route tables) shall set this field to 0000h.

The ACTIVE ZONE MANAGER SAS ADDRESS field indicates the SAS address of the zone manager that last locked the zoning expander device. If the zoning expander device is currently being configured by a vendor-specific sideband method then the ACTIVE ZONE MANAGER SAS ADDRESS field shall be set to zero. This field shall be set to zero at power on.

The ZONE LOCK INACTIVITY TIME LIMIT field indicates the minimum time between any SMP ZONE LOCK requests, SMP zone configuration function requests, or SMP ZONE ACTIVATE requests from the active zone manager that the locked expander device allows and is set in the SMP ZONE LOCK request (see 10.4.3.18).

The FIRST ENCLOSURE CONNECTOR ELEMENT INDEX field indicates the lowest CONNECTOR ELEMENT INDEX field of all the expander phys in all the expander devices in the enclosure that have CONNECTOR TYPE fields set to 20h through 2Fh (i.e., an internal connector to an end device) in their SMP DISCOVER responses.

The NUMBER OF ENCLOSURE CONNECTOR ELEMENT INDEXES field indicates the number of expander phys in all the expander devices in the enclosure that have CONNECTOR TYPE fields set to 20h through 2Fh (i.e., an internal connector to an end device) in their SMP DISCOVER responses.

NOTE 84 - The NUMBER OF ENCLOSURE CONNECTOR ELEMENT INDEXES field assumes that all internal connectors to end devices are assigned to a contiguous range of CONNECTOR ELEMENT INDEX field values.

A REDUCED FUNCTIONALITY bit set to one indicates that:

- a) the expander device is scheduled to reduce its functionality (see 4.6.8) in the time indicated in the TIME TO REDUCED FUNCTIONALITY field; or
- b) that the expander device is currently operating with reduced functionality (see 4.6.8).

A REDUCED FUNCTIONALITY bit set to zero indicates the expander device is not scheduled to reduce functionality and that the contents of the TIME TO REDUCED FUNCTIONALITY field shall be ignored.

If the REDUCED FUNCTIONALITY bit set to one, then the TIME TO REDUCED FUNCTIONALITY field contains the time, in 100 ms increments, remaining until the expander device is scheduled to reduce functionality. The expander device starts the reduced functionality delay timer after originating a Broadcast (Expander) (see 4.6.8).

The INITIAL TIME TO REDUCED FUNCTIONALITY field contains the minimum period of time, in 100 ms increments, that an expander device waits from originating a Broadcast (Expander) to reducing functionality. The expander device should set the default value for the INITIAL TIME TO REDUCED FUNCTIONALITY field to at least 2 000 ms (i.e., 14h).

The MAXIMUM REDUCED FUNCTIONALITY TIME field contains the maximum time, in seconds, that the expander device responds with OPEN\_REJECT (RETRY) to connection requests that map to an expander phy or an SMP target port that is not accessible during expander device reduced functionality. This timer starts after the reduced functionality delay timer expires.

The LAST PHY EVENT INFORMATION DESCRIPTOR INDEX field indicates the last index of the last recorded phy event information descriptor.

The CRC field is defined in 10.4.3.2.

#### **9.4.5.4 REPORT PHY EVENT INFORMATION function**

##### **9.4.5.4.1 REPORT PHY EVENT INFORMATION function overview**

The REPORT PHY EVENT INFORMATION function returns phy event information (see 4.11) about the specified phy. This SMP function may implemented by any management device server.

9.4.5.4.2 REPORT PHY EVENT INFORMATION request

Table 183 defines the request format.

Table 183 — REPORT PHY EVENT INFORMATION request

Byte\Bit	7	6	5	4	3	2	1	0
0	SMP FRAME TYPE (40h)							
1	FUNCTION (14h 20h)							
2	Reserved							
3	REQUEST LENGTH (02h)							
4	Reserved							
5	Reserved							
8	Reserved							
9	PHY IDENTIFIER							
9	Reserved				DESCRIPTOR TYPE			
10	Reserved							
10	(MSB)	STARTING PHY EVENT INFORMATION DESCRIPTOR INDEX						(LSB)
11								
12	(MSB)	CRC						(LSB)
15								

The SMP FRAME TYPE field shall be set to 40h.

The FUNCTION field shall be set to 14h.

The REQUEST LENGTH field contains the number of dwords that follow, not including the CRC field (i.e., 2).

The PHY IDENTIFIER field specifies the phy (see 4.2.7) for which information shall be reported.

The DESCRIPTOR TYPE field is defined in Table 183 and specifies the PHY EVENT INFORMATION descriptor format and length.

The STARTING PHY EVENT INFORMATION DESCRIPTOR INDEX field specifies the first phy event information descriptor that the management device server shall return in the SMP response frame. A STARTING PHY EVENT INFORMATION DESCRIPTOR INDEX of 00h is reserved. Descriptor indexes shall roll over to an index of at least 01h. The management device server may return any number of phy event information descriptors in the response list.

The CRC field is defined in 10.4.3.1.

**Table 184 — DESCRIPTOR TYPE field**

<b>Code</b>	<b>PHY EVENT INFORMATION descriptor format</b>	<b>Descriptor length</b>
0h	<u>Defined in Table 185</u>	<u>03h</u>
All others	Reserved	

**9.4.5.4.3 REPORT PHY EVENT INFORMATION response**

Table 247 defines the response format.



Table 185 — REPORT PHY EVENT INFORMATION response

Byte/Bit	7	6	5	4	3	2	1	0
0	SMP FRAME TYPE (41h)							
1	FUNCTION (14h 20h)							
2	FUNCTION RESULT							
3	RESPONSE LENGTH							
4	(MSB)	EXPANDER CHANGE COUNT						(LSB)
5	Reserved							
6	(MSB)	STARTING PHY EVENT INFORMATION DESCRIPTOR INDEX						(LSB)
7	Reserved							
8	DESCRIPTOR LENGTH							
9	Reserved				DESCRIPTOR TYPE			
9	PHY IDENTIFIER							
10	(MSB)	TOTAL NUMBER OF PHY EVENT INFORMATION DESCRIPTORS						(LSB)
11	Reserved							
12	(MSB)	LAST PHY EVENT INFORMATION DESCRIPTOR INDEX						(LSB)
13	Reserved							
14	(MSB)	MAXIMUM NUMBER OF STORED DESCRIPTORS						(LSB)
15	Reserved							
16	Reserved							
18	Reserved							
19	NUMBER OF PHY EVENT DESCRIPTORS							
Phy event descriptor list								
16	Phy event descriptor (first)(see table 186 in 9.4.5.4.4)							
27	...							
n - 15	Phy event descriptor (last)(see table 186 in 9.4.5.4.4)							
n - 4	...							

**Table 185 — REPORT PHY EVENT INFORMATION response**

Byte/Bit	7	6	5	4	3	2	1	0
n - 3	(MSB)							
	CRC							
n	(LSB)							

The SMP FRAME TYPE field shall be set to 41h.

The FUNCTION field shall be set to 14h.

The FUNCTION RESULT field is defined in 10.4.3.2.

The RESPONSE LENGTH field contains the number of dwords that follow, not including the CRC field.

The EXPANDER CHANGE COUNT field is defined in the SMP REPORT GENERAL response (see 10.4.3.3).

The PHY IDENTIFIER field indicates the phy (see 4.2.7) for which information is being reported.

The STARTING PHY EVENT INFORMATION DESCRIPTOR INDEX field indicates the index of the first phy event information descriptor being returned, and is set to the same value as the STARTING PHY EVENT INFORMATION DESCRIPTOR INDEX field in the SMP request frame, unless the requested index is invalid. A value of 0000h shall indicate that the requested starting log index was invalid.

The DESCRIPTOR LENGTH field indicates the length of the REPORT PHY EVENT INFORMATION descriptor (see Table 183).

The DESCRIPTOR TYPE field is defined in and specifies the REPORT PHY EVENT INFORMATION descriptor format and length and is defined in Table 183.

The TOTAL NUMBER OF PHY EVENT INFORMATION DESCRIPTORS field indicates how many phy event information descriptors are available at this time from the management device server.

The LAST PHY EVENT INFORMATION DESCRIPTOR INDEX is defined in the SMP REPORT GENERAL response (see 10.4.3.3).

Device management servers shall support indexes through 65 536. After the maximum index is used the device management server shall roll the index counter to at least 0001h.

The MAXIMUM NUMBER OF STORED DESCRIPTORS field indicates the maximum number of PHY EVENT INFORMATION descriptors, of the type specified in the PHY EVENT INFORMATION request, that the management device server stores.

NOTE 85 - If there are no free memory locations to store a new PHY EVENT INFORMATION log, the management device server shall replace the oldest PHY EVENT INFORMATION log. This means that PHY EVENT INFORMATION logs will be lost if the application client fails to request PHY EVENT INFORMATION logs before the management device must overwrite some unread log entries.

The NUMBER OF PHY EVENT DESCRIPTORS field indicates how many phy event descriptors follow.

The phy event descriptor list contains phy event descriptors as defined in 9.4.5.4.4.

The CRC field is defined in 10.4.3.2.

## 9.4.5.4.4 REPORT PHY EVENT INFORMATION response phy event descriptor

Table 186 defines the phy event descriptor.

**Table 186 — Phy event descriptor format 0h**

Byte\Bit	7	6	5	4	3	2	1	0
0	Reserved							
2	PHY IDENTIFIER							
3	PHY EVENT INFORMATION SOURCE							
4	(MSB)	PHY EVENT INFORMATION						(LSB)
7								
8	(MSB)	PEAK VALUE DETECTOR THRESHOLD						(LSB)
11								

The PHY IDENTIFIER field indicates the phy for which information is being returned.

The PHY EVENT INFORMATION SOURCE field, defined in table 31 in 4.11, indicates the type of phy event information being reported in the PHY EVENT INFORMATION field.

The PHY EVENT INFORMATION field contains the value (i.e., the count or peak value detected) of the phy event indicated by the phy event information source field.

If the phy event information source is a peak value detector, the PEAK VALUE DETECTOR THRESHOLD field contains the value of the peak value detector that causes the expander device to originate a Broadcast (Expander)(see 7.2.5.5). If the phy event information source is not a peak value detector, then the PEAK VALUE DISCOVER LIST function

### 9.4.5.4.5 DISCOVER LIST response

Table 187 defines the response format.

**Table 187 — DISCOVER LIST response**

Byte\Bit	7	6	5	4	3	2	1	0
0	SMP FRAME TYPE (41h)							
1	FUNCTION (16h)							
2	FUNCTION RESULT							
3	RESPONSE LENGTH ((n - 7) / 4)							
4	(MSB)	EXPANDER CHANGE COUNT						(LSB)
5								
6	Reserved							
7								
8	STARTING PHY IDENTIFIER							
9	NUMBER OF DISCOVER LIST DESCRIPTORS							
10	Reserved				PHY FILTER			
11	Reserved				DESCRIPTOR TYPE			
12	DESCRIPTOR LENGTH							
13								
15	Reserved							
16	ZONING SUPPORTED	ZONING ENABLED	Reserved			CONFIGURING	EXTERNALLY CONFIGURABLE ROUTE TABLE	
17	Reserved							
18								
19	(MSB)	LAST PHY EVENT INFORMATION DESCRIPTOR INDEX						(LSB)
20								
21	Reserved							
31								
32	Vendor specific							
47								
DISCOVER LIST descriptor list								
48	DISCOVER LIST descriptor (first)(see table 184 in 9.4.5.4.5, and table 236 in 10.4.3.7 or table 188 in 9.4.5.4.8)							
	...							
n - 4	DISCOVER LIST descriptor (last)(see table 184 in 9.4.5.4.5, and table 236 in 10.4.3.7 or table 188 in 9.4.5.4.8)							
n - 3	(MSB)	CRC						(LSB)
n								

The SMP FRAME TYPE field shall be set to 41h.

The FUNCTION field shall be set to 16h.

The FUNCTION RESULT field is defined in 10.4.3.2.

The RESPONSE LENGTH field contains the number of dwords that follow not including the CRC field.

The EXPANDER CHANGE COUNT field is defined in the SMP REPORT GENERAL response (see 10.4.3.3).

The STARTING PHY IDENTIFIER field indicates the phy identifier of the first phy in the DISCOVER LIST descriptor list.

NOTE 86 - The STARTING PHY IDENTIFIER field may be different than the STARTING PHY IDENTIFIER field in the request frame (see 10.4.3.13.2) due to the filter specified by the PHY FILTER field in the request frame.

The NUMBER OF DISCOVER LIST DESCRIPTORS field indicates the number of DISCOVER LIST descriptors returned in the DISCOVER LIST descriptor list.

The DESCRIPTOR LENGTH field indicates the length of the DISCOVER LIST descriptor (see table 184 in 10.4.3.13.2).

The LAST PHY EVENT INFORMATION DESCRIPTOR INDEX is defined in the SMP REPORT GENERAL response (see 10.4.3.3).

The ZONING SUPPORTED bit is defined in the SMP REPORT GENERAL response (see 10.4.3.3).

The ZONING ENABLED bit is defined in the SMP REPORT GENERAL response (see 10.4.3.3).

The CONFIGURING bit is defined in the SMP DISCOVER response (see 10.4.3.7).

The CONFIGURABLE ROUTE TABLE bit is defined in the SMP DISCOVER response (see 10.4.3.7).

The DISCOVER LIST descriptor list contains DISCOVER LIST descriptors for each phy:

- a) starting with the phy whose phy identifier is specified in the STARTING PHY IDENTIFIER field in the request (see 10.4.3.13.2);
- b) satisfying the filter specified in the PHY FILTER field in the request (see table 258 in 10.4.3.13.2); and
- c) that is able to be included in the response frame without being truncated.

Each DISCOVER LIST descriptor shall use the format specified in the DESCRIPTOR TYPE field in the request (see table 184 in 10.4.3.13.2)

The management device server shall not include DISCOVER LIST descriptors for phys with phy identifiers greater than or equal to the NUMBER OF PHYS field reported in the SMP REPORT GENERAL response (see 10.4.3.3). The management device server shall not include partial DISCOVER LIST descriptors.

The CRC field is defined in 10.4.3.2.