

T10/08-047r3 SMC-3 New Tape Alert flags

To: T10 Technical Committee
From: Noud Snelder, BDT (noud.snelder@bdt.de)
Date: 20 August 2008
Subject: T10/08-047r3 SMC-3 New Tape Alert flags

Revision History

Revision 0 (04 January 2008): initial revision
Revision 1 (27 April 2008): incorporated comments from Rod Wideman
Revision 2 (16 July 2008): incorporated comments from July SMC-3 WG meeting
Revision 3 (20 August 2008): incorporated comments from SMC-3 telephone conference

Related Documents

SMC-3 r10 - SCSI Media Changer Commands – 3, revision 10

Overview

The media changer tape alert flags report about certain events/error conditions within the media changer. This proposal creates four new flags for specific error conditions that currently have no dedicated flag. [Removed Media Transport Element Full flag, because there is a proposal with a unique sense code for this event. Renamed Library Inventory Overloaded to Library Capacity Exceeded.](#)

Changes to SMC3:

Add the following tape alert flags to table A.1:

Code	Flag	Type	Flag Type	Recommended application client message	Probable cause
21h	Library Capacity Exceeded	O	C	The total number of volumes exceeds the available number of storage elements. Remove a cartridge from the inventory to recover.	User filled all storage elements inserted full magazines while there was a cartridge in the drive
22h	No Cleaning Cartridge	O	W	The library is managing cleaning of the tape drive(s), but there is no cleaning cartridge available in the inventory. Add a cleaning cartridge to the inventory to recover.	No cleaning cartridge available
23h	Expired Cleaning Cartridge	O	W	At least one of the cleaning cartridges has expired. Replace the expired cleaning cartridge with a new cleaning cartridge to recover.	Expired cleaning cartridge