

Date: July 16, 2008

To: T10 Committee (SCSI)

From: George Penokie (LSI)

Subject: SBC-3 SPC-4: Protection Type 3 Reference Tag Clarification

1 Overview

When type 3 data protection is used the logical block reference tag should follow the same rules as the logical block application tag when it comes to the rules on whether or not it may be modified by the device server. To make this clear the following changes should be made to SBC-3 and SPC-4.

2 SBC-3 changes

2.0.1 Protection types

2.0.1.1 Protection types overview

The content of protection information is dependent on the type of protection to which a logical unit has been formatted.

The type of protection supported by the logical unit shall be indicated in the SPT field in the Extended INQUIRY Data VPD page (see SPC-4). The current protection type shall be indicated in the P_TYPE field in the READ CAPACITY(16) command (see 5.13).

An application client may format the logical unit to a specific type of protection using the ~~RTO_REQ bit~~ FMTINFO field and PROTECTION FIELD USAGE field in the FORMAT UNIT command (see 5.2).

...

2.0.2 Protection information format

Table 1 defines the placement of protection information in a logical block.

Table 1 — User data and protection information format

Byte/Bit	7	6	5	4	3	2	1	0	
0	USER DATA								
n - 1	USER DATA								
n	(MSB)	LOGICAL BLOCK GUARD							
n + 1		LOGICAL BLOCK GUARD							(LSB)
n + 2	(MSB)	LOGICAL BLOCK APPLICATION TAG							
n + 3		LOGICAL BLOCK APPLICATION TAG							(LSB)
n + 4	(MSB)	LOGICAL BLOCK REFERENCE TAG							
n + 7		LOGICAL BLOCK REFERENCE TAG							(LSB)

The USER DATA field shall contain user data. The contents of the USER DATA field shall be used to generate and check the CRC contained in the LOGICAL BLOCK GUARD field.

The LOGICAL BLOCK GUARD field contains the CRC (see 4.17.4) of the contents of the USER DATA field.

The LOGICAL BLOCK APPLICATION TAG field is set by the application client. If the device server detects a:

- a) LOGICAL BLOCK APPLICATION TAG field set to FFFFh and type 1 protection (see 4.17.2.3) or type 2 protection (see 4.17.2.4) is enabled; or
- b) LOGICAL BLOCK APPLICATION TAG field set to FFFFh, LOGICAL BLOCK REFERENCE TAG field set to FFFF FFFFh, and type 3 protection (see 4.17.2.5) is enabled,

then the device server disables checking of all protection information for the logical block when reading from the medium. Otherwise, the contents of the logical block application tag are not defined by this standard.

The LOGICAL BLOCK APPLICATION TAG field may be modified by a device server if the ATO bit is set to zero in the Control mode page (see SPC-4). If the ATO bit is set to one in the Control mode page, then the device server shall not modify the LOGICAL BLOCK APPLICATION TAG field.

The contents of the LOGICAL BLOCK APPLICATION TAG field shall not be used to generate or check the CRC contained in the LOGICAL BLOCK GUARD field.

The LOGICAL BLOCK REFERENCE TAG field of the first logical block in the data-in buffer and/or data-out buffer shall contain the value specified in table 2.

Table 2 — Contents of the LOGICAL BLOCK REFERENCE TAG field of the first logical block in the data-in buffer and/or data-out buffer

Protection Type	Content of the LOGICAL BLOCK REFERENCE TAG field of the first logical block in the data-in buffer and/or data-out buffer
Type 1 protection (see 4.17.2.3)	The least significant four bytes of the LBA contained in the LOGICAL BLOCK ADDRESS field of the command.
Type 2 protection (see 4.17.2.4)	The value in the EXPECTED INITIAL LOGICAL BLOCK REFERENCE TAG field of the command.
Type 3 protection (see 4.17.2.5)	Not defined in this standard. <u>May be modified by the device server if the ATO bit is set to zero in the Control mode page (see SPC-4). If the ATO bit is set to one in the Control mode page, then the device server shall not modify this field.</u>

The LOGICAL BLOCK REFERENCE TAG field subsequent logical blocks in the data-in buffer and/or data-out buffer shall be set as specified in table 3.

Table 3 — Setting the LOGICAL BLOCK REFERENCE TAG field of the subsequent logical blocks in the data-in buffer and/or data-out buffer

Protection Type	The content of the LOGICAL BLOCK REFERENCE TAG field of each subsequent logical block in the data-in buffer and/or data-out buffer
Type 1 protection (see 4.17.2.3) and Type 2 protection (see 4.17.2.4)	The logical block reference tag of the previous logical block plus one.
Type 3 protection (see 4.17.2.5)	Not defined in this standard. <u>May be modified by the device server if the ATO bit is set to zero in the Control mode page (see SPC-4). If the ATO bit is set to one in the Control mode page, then the device server shall not modify this field.</u>

The contents of the LOGICAL BLOCK REFERENCE TAG field shall not be used to generate or check the CRC contained in the LOGICAL BLOCK GUARD field.

2.1 FORMAT UNIT command

2.1.1 FORMAT UNIT command overview

The FORMAT UNIT command (see table 4) requests that the device server format the medium into application client accessible logical blocks as specified in the number of logical blocks and logical block length values received in the last mode parameter block descriptor (see 6.3.2) in a MODE SELECT command (see SPC-4). In addition, the device server may certify the medium and create control structures for the management of the medium and defects. The degree that the medium is altered by this command is vendor-specific.

If a device server receives a FORMAT UNIT command before receiving a MODE SELECT command with a mode parameter block descriptor the device server shall use the number of logical blocks and logical block length at which the logical unit is currently formatted (i.e., no change is made to the number of logical blocks and the logical block length of the logical unit during the format operation).

If any deferred downloaded code has been received as a result of a WRITE BUFFER command (see SPC-4), then that deferred downloaded code shall replace the current operational code.

Table 4 — FORMAT UNIT command

Byte/Bit	7	6	5	4	3	2	1	0
0	OPERATION CODE (04h)							
1	FMTPINFO_ RTO_REQ		LONGLIST	FMTDATA	CMPLST	DEFECT LIST FORMAT		
2	Vendor-specific							
3	Obsolete							
4	Obsolete							
5	CONTROL							

...

A format protection information (FMTPINFO) **bitfield** (see table 7) **in combination with the PROTECTION FIELD USAGE field (see 2.1.2.2)** specifies if the device server enables or disables the use of protection information.

~~The reference tag own request (RTO_REQ) bit (see table 7) specifies whether the application client or the device server has ownership of the LOGICAL BLOCK REFERENCE TAG field in protection information (see 4.17.3).~~

Following a successful format, the P_TYPE field in the READ CAPACITY (16) parameter data (see 5.13.1) indicates the type of protection currently in effect on the logical unit.

When protection information is written during a FORMAT UNIT command (i.e., the FMTPINFO **bitfield** is set to **one a value greater than zero**) protection information shall be written to a default value of FFFFFFFF_FFFFFFFFh.

...

2.1.2 FORMAT UNIT parameter list

2.1.2.1 FORMAT UNIT parameter list overview

....

2.1.2.2 Parameter list header

....

Table 5 — Short parameter list header

Byte\Bit	7	6	5	4	3	2	1	0
0	Reserved					PROTECTION FIELD USAGE		
1	FOV	DPRY	DCRT	STPF	IP	Obsolete	IMMED	Vendor-specific
2	(MSB) _____							
3	DEFECT LIST LENGTH _____ (LSB)							

The long parameter list header (see table 6) is used if the `LONGLIST` bit is set to one in the `FORMAT UNIT CDB`.

Table 6 — Long parameter list header

Byte\Bit	7	6	5	4	3	2	1	0
0	Reserved					PROTECTION FIELD USAGE		
1	FOV	DPRY	DCRT	STPF	IP	Obsolete	IMMED	Vendor-specific
2	Reserved							
3	Reserved							
4	(MSB) _____							
7	DEFECT LIST LENGTH _____ (LSB)							

The `PROTECTION FIELD USAGE` field in combination with the `FMPINFO` ~~bit and the `RTO_REQ` bit~~field (see table 7) specifies the requested protection type (see 4.17.2)

Table 7 — FMT PINFO ~~bit, RTO_REQ bit,~~ field and PROTECTION FIELD USAGE field

Device server indication		Application client specification		Description
SPT ^a	PROTECT ^b	FMT PINFO	PROTECTION FIELD USAGE	
xxx _b	0	<u>00</u> _b	000 _b	The logical unit shall be formatted to type 0 protection ^c (see 4.17.2.2) resulting in the P_TYPE field ^d being set to 000 _b .
xxx _b	0	<u>00</u> _b	>000 _b	Illegal ^e
xxx _b	0	<u>01</u> _b	xxx _b	Illegal ^f
xxx _b	0	<u>1x</u> _b	xxx _b	Illegal ^f
xxx _b	1	<u>00</u> _b	000 _b	The logical unit shall be formatted to type 0 protection ^c (see 4.17.2.2) resulting in the P_TYPE field ^d being set to 000 _b .
xxx _b	1	<u>00</u> _b	>000 _b	Illegal ^e
xxx _b	1	<u>01</u> _b	xxx _b	Illegal ^f
000 _b 001 _b 011 _b	1	<u>10</u> _b	000 _b	The logical unit shall be formatted to type 1 protection ^g (see 4.17.2.3) resulting in the P_TYPE field ^d being set to 000 _b .
000 _b 001 _b 011 _b	1	<u>10</u> _b	>000 _b	Illegal ^e
000 _b	1	<u>11</u> _b	xxx _b	Illegal ^f
001 _b	1	<u>11</u> _b	000 _b	The logical unit shall be formatted to type 2 protection ^g (see 4.17.2.4) resulting in the P_TYPE field ^d being set to 001 _b .
001 _b	1	<u>11</u> _b	>000 _b	Illegal ^e
011 _b	1	<u>11</u> _b	000 _b	Illegal ^e
011 _b	1	<u>11</u> _b	001 _b	The logical unit shall be formatted to type 3 protection. ^g (see 4.17.2.5) resulting in the P_TYPE field ^d being set to 010 _b .
011 _b	1	<u>11</u> _b	>001 _b	Illegal ^e
010 _b	1	<u>1x</u> _b	xxx _b	Reserved
1xx _b	1	<u>1x</u> _b	xxx _b	Reserved

^a See the Extended INQUIRY Data VPD page (see SPC-4) for the definition of the SPT field.
^b See the standard INQUIRY data (see SPC-4) for the definition of the PROTECT bit.
^c The device server shall format the medium to the logical block length specified in the mode parameter block descriptor of the mode parameter header (see SPC-4).
^d See the READ CAPACITY command (see 5.13.1) for the definition of the P_TYPE field.
^e The device server shall terminate the command with CHECK CONDITION status with the sense key set to ILLEGAL REQUEST and the additional sense code set to INVALID FIELD IN PARAMETER LIST.
^f The device server shall terminate the command with CHECK CONDITION status with the sense key set to ILLEGAL REQUEST and the additional sense code set to INVALID FIELD IN CDB.
^g The device server shall format the medium to the logical block length specified in the mode parameter block descriptor of the mode parameter header plus eight (e.g., if the logical block length is 512, then the formatted logical block length is 520). Following a successful format, the PROT_EN bit in the READ CAPACITY (16) parameter data (see 5.13.1) indicates whether protection information (see 4.17) is enabled.

...

2.2 ORWRITE command

....

Table 8 — ORPROTECT field - checking protection information from the data-out buffer (part 1 of 2)

Code	Logical unit formatted with protection information	Field in protection information	Device server check	If check fails ^{d e} , additional sense code
000b	Yes	No protection information received from application client to check		
	No	No protection information received from application client to check		
001b ^b	Yes	LOGICAL BLOCK GUARD	Shall	LOGICAL BLOCK GUARD CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG	May ^c	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
		LOGICAL BLOCK REFERENCE TAG	Shall <u>(except for type 3)</u> ^f	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
	No	Error condition ^a		
010b ^b	Yes	LOGICAL BLOCK GUARD	Shall not	No check performed
		LOGICAL BLOCK APPLICATION TAG	May ^c	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
		LOGICAL BLOCK REFERENCE TAG	May ^f	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
	No	Error condition ^a		
011b ^b	Yes	LOGICAL BLOCK GUARD	Shall not	No check performed
		LOGICAL BLOCK APPLICATION TAG	Shall not	No check performed
		LOGICAL BLOCK REFERENCE TAG	Shall not	No check performed
	No	Error condition ^a		
100b ^b	Yes	LOGICAL BLOCK GUARD	Shall	LOGICAL BLOCK GUARD CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG	Shall not	No check performed
		LOGICAL BLOCK REFERENCE TAG	Shall not	No check performed
	No	Error condition ^a		

Table 8 — ORPROTECT field - checking protection information from the data-out buffer (part 2 of 2)

Code	Logical unit formatted with protection information	Field in protection information	Device server check	If check fails ^{d e} , additional sense code
101b ^b	Yes	LOGICAL BLOCK GUARD	Shall	LOGICAL BLOCK GUARD CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG	May ^c	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
		LOGICAL BLOCK REFERENCE TAG	May ^f	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
	No	Error condition ^a		
110b-111b	Reserved			

^a An or write operation to a logical unit that supports protection information (see 4.17) and has not been formatted with protection information shall be terminated with CHECK CONDITION status with the sense key set to ILLEGAL REQUEST and the additional sense code set to INVALID FIELD IN CDB.

^b If the logical unit does not support protection information the requested command should be terminated with CHECK CONDITION status with the sense key set to ILLEGAL REQUEST and the additional sense code set to INVALID FIELD IN CDB.

^c The device server may check the logical block application tag if the ATO bit is set to one in the Control mode page (see SPC-4) and if it has knowledge of the contents of the LOGICAL BLOCK APPLICATION TAG field. This knowledge is obtained by a method not defined by this standard.

^d If an error is reported, the sense key shall be set to ABORTED COMMAND.

^e If multiple errors occur, the selection of which error to report is not defined by this standard.

^f If type 1 protection is enabled, the device server ~~shall check~~ the logical block reference tag by comparing it to the lower 4 bytes of the LBA associated with the logical block. If type 3 protection is enabled, the ATO bit is set to one in the Control mode page (see SPC-4), and the device server has knowledge of the contents of the LOGICAL BLOCK REFERENCE TAG field, then the device server may ~~checks the logical block reference tag~~ checks ~~if it has knowledge of the contents of the LOGICAL BLOCK REFERENCE TAG field.~~ The method for acquiring this knowledge is not defined by this standard.

2.3 READ (10) command

...

Table 9 — RDPROTECT field (part 1 of 3)

Code	Logical unit formatted with protection information	Shall device server transmit protection information?	Field in protection information ^h	Extended INQUIRY Data VPD page bit value ^g	If check fails ^{d f} , additional sense code
000b	Yes	No	LOGICAL BLOCK GUARD	GRD_CHK = 1	LOGICAL BLOCK GUARD CHECK FAILED
				GRD_CHK = 0	No check performed
			LOGICAL BLOCK APPLICATION TAG	APP_CHK = 1 ^c	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
				APP_CHK = 0	No check performed
			LOGICAL BLOCK REFERENCE TAG	REF_CHK = 1 ⁱ	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
	REF_CHK = 0	No check performed			
No	No protection information available to check				
001b 101b ^b	Yes	Yes ^e	LOGICAL BLOCK GUARD	GRD_CHK = 1	LOGICAL BLOCK GUARD CHECK FAILED
				GRD_CHK = 0	No check performed
			LOGICAL BLOCK APPLICATION TAG	APP_CHK = 1 ^c	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
				APP_CHK = 0	No check performed
			LOGICAL BLOCK REFERENCE TAG	REF_CHK = 1 ⁱ	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
	REF_CHK = 0	No check performed			
No ^a	No protection information available to transmit to the data-in buffer or for checking				

Table 9 — RDPROTECT field (part 2 of 3)

Code	Logical unit formatted with protection information	Shall device server transmit protection information?	Field in protection information ^h	Extended INQUIRY Data VPD page bit value ^g	If check fails ^{d f} , additional sense code
010b ^b	Yes	Yes ^e	LOGICAL BLOCK GUARD	No check performed	
			LOGICAL BLOCK APPLICATION TAG	APP_CHK = 1 ^c	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
				APP_CHK = 0	No check performed
			LOGICAL BLOCK REFERENCE TAG	REF_CHK = 1 ⁱ	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
	REF_CHK = 0	No check performed			
No ^a	No protection information available to transmit to the data-in buffer or for checking				
011b ^b	Yes	Yes ^e	LOGICAL BLOCK GUARD	No check performed	
			LOGICAL BLOCK APPLICATION TAG	No check performed	
			LOGICAL BLOCK REFERENCE TAG	No check performed	
	No ^a	No protection information available to transmit to the data-in buffer or for checking			
100b ^b	Yes	Yes ^e	LOGICAL BLOCK GUARD	GRD_CHK = 1	LOGICAL BLOCK GUARD CHECK FAILED
				GRD_CHK = 0	No check performed
			LOGICAL BLOCK APPLICATION TAG	No check performed	
			LOGICAL BLOCK REFERENCE TAG	No check performed	
	No ^a	No protection information available to transmit to the data-in buffer or for checking			
110b - 111b	Reserved				

Table 9 — RDPROTECT field (part 3 of 3)

Code	Logical unit formatted with protection information	Shall device server transmit protection information?	Field in protection information ^h	Extended INQUIRY Data VPD page bit value ^g	If check fails ^{d f} , additional sense code
<p>^a A read operation to a logical unit that supports protection information (see 4.17) and has not been formatted with protection information shall be terminated with CHECK CONDITION status with the sense key set to ILLEGAL REQUEST and the additional sense code set to INVALID FIELD IN CDB.</p> <p>^b If the logical unit does not support protection information the requested command should be terminated with CHECK CONDITION status with the sense key set to ILLEGAL REQUEST and the additional sense code set to INVALID FIELD IN CDB.</p> <p>^c The device server shall check the logical block application tag if it has knowledge of the contents of the LOGICAL BLOCK APPLICATION TAG field. If the READ (32) command (see 5.11) is used and the ATO bit is set to one in the Control mode page (see SPC-4), this knowledge is acquired from the EXPECTED LOGICAL BLOCK APPLICATION TAG field and the LOGICAL BLOCK APPLICATION TAG MASK field in the CDB. Otherwise, this knowledge may be acquired by a method not defined by this standard.</p> <p>^d If an error is reported, the sense key shall be set to ABORTED COMMAND.</p> <p>^e Transmit protection information to the data-in buffer.</p> <p>^f If multiple errors occur, the selection of which error to report is not defined by this standard.</p> <p>^g See the Extended INQUIRY Data VPD page (see SPC-4) for the definitions of the GRD_CHK bit, the APP_CHK bit, and the REF_CHK bit.</p> <p>^h If the device server detects a:</p> <p>a) LOGICAL BLOCK APPLICATION TAG field set to FFFFh and type 1 protection (see 4.17.2.3) or type 2 protection (see 4.17.2.4) is enabled; or</p> <p>b) LOGICAL BLOCK APPLICATION TAG field set to FFFFh, LOGICAL BLOCK REFERENCE TAG field set to FFFF FFFFh, and type 3 protection (see 4.17.2.5) is enabled,</p> <p>then the device server shall not check any protection information in the associated logical block.</p> <p>ⁱ If type 1 protection is enabled, the device server checks the logical block reference tag by comparing it to the lower 4 bytes of the LBA associated with the logical block. If type 2 protection or type 3 protection is enabled, the device server checks the logical block reference tag if it has knowledge of the contents of the LOGICAL BLOCK REFERENCE TAG field. If type 2 protection is enabled, then this knowledge may be acquired through the EXPECTED INITIAL LOGICAL BLOCK REFERENCE TAG field in a READ (32) command (see 5.11). If type 3 protection is enabled, then the method for acquiring this knowledge is not defined by this standard.</p>					

2.4 VERIFY (10) command

....

Table 10 — VRPROTECT field with BYTCHK set to one - checking protection information from the data-out buffer (part 1 of 2)

Code	Logical unit formatted with protection information	Field in protection information	Device server check	If check fails ^{d e} , additional sense code
000b	Yes	No protection information received from application client to check		
	No	No protection information received from application client to check		
001b ^b	Yes	LOGICAL BLOCK GUARD	Shall	LOGICAL BLOCK GUARD CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG	May ^c	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
		LOGICAL BLOCK REFERENCE TAG	Shall (except for type 3) ^f	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
	No	Error condition ^a		
010b ^b	Yes	LOGICAL BLOCK GUARD	Shall not	No check performed
		LOGICAL BLOCK APPLICATION TAG	May ^c	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
		LOGICAL BLOCK REFERENCE TAG	May ^f	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
	No	Error condition ^a		
011b ^b	Yes	LOGICAL BLOCK GUARD	Shall not	No check performed
		LOGICAL BLOCK APPLICATION TAG	Shall not	No check performed
		LOGICAL BLOCK REFERENCE TAG	Shall not	No check performed
	No	Error condition ^a		
100b ^b	Yes	LOGICAL BLOCK GUARD	Shall	LOGICAL BLOCK GUARD CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG	Shall not	No check performed
		LOGICAL BLOCK REFERENCE TAG	Shall not	No check performed
	No	Error condition ^a		

Table 10 — VRPROTECT field with BYTCHK set to one - checking protection information from the data-out buffer (part 2 of 2)

Code	Logical unit formatted with protection information	Field in protection information	Device server check	If check fails ^{d e} , additional sense code
101b ^b	Yes	LOGICAL BLOCK GUARD	Shall	LOGICAL BLOCK GUARD CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG	May ^c	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
		LOGICAL BLOCK REFERENCE TAG	May ^f	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
	No	Error condition ^a		
110b-111b	Reserved			

^a A verify operation to a logical unit that supports protection information (see 4.17) and has not been formatted with protection information shall be terminated with CHECK CONDITION status with the sense key set to ILLEGAL REQUEST and the additional sense code set to INVALID FIELD IN CDB.

^b If the logical unit does not support protection information the requested command should be terminated with CHECK CONDITION status with the sense key set to ILLEGAL REQUEST and the additional sense code set to INVALID FIELD IN CDB.

^c The device server may check the logical block application tag if the ATO bit is set to one in the Control mode page (see SPC-4) and if it has knowledge of the contents of the LOGICAL BLOCK APPLICATION TAG field. If the VERIFY (32) command (see 5.25) is used, this knowledge is obtained from the EXPECTED LOGICAL BLOCK APPLICATION TAG field and the LOGICAL BLOCK APPLICATION TAG MASK field in the CDB. Otherwise, this knowledge is obtained by a method not defined by this standard.

^d If an error is reported, the sense key shall be set to ABORTED COMMAND.

^e If multiple errors occur, the selection of which error to report is not defined by this standard.

^f If type 1 protection is enabled, the device server ~~shall check~~ the logical block reference tag by comparing it to the lower 4 bytes of the LBA associated with the logical block. If type 2 protection ~~or type 3 protection is enabled~~ enabled, and the device server has knowledge of the contents of the LOGICAL BLOCK REFERENCE TAG field, then the device server checks the logical block reference tag ~~if it has knowledge of the contents of the LOGICAL BLOCK REFERENCE TAG field.~~ If type 2 protection is enabled, then this knowledge may be acquired through the EXPECTED INITIAL LOGICAL BLOCK REFERENCE TAG field in a VERIFY (32) command (see 5.25). If type 3 protection is enabled, the ATO bit is set to one in the Control mode page (see SPC-4), and the device server has knowledge of the contents of the LOGICAL BLOCK REFERENCE TAG field, then the device server may check the logical block reference tag. If type 3 protection is enabled, then the method for acquiring this knowledge is not defined by this standard.

If the BYTCHK bit is set to one, the device server shall perform a byte-by-byte comparison of protection information transferred from the data-out buffer with protection information read from the medium based on the VRPROTECT field as described in table 11.

Table 11 — VRPROTECT field with BYTCHK set to one - byte-by-byte comparison requirements (part 1 of 2)

Code	Logical unit formatted with protection information	Field	Byte-by-byte Comparison	If compare fails ^{c d} , additional sense code
000b	Yes	No protection information received from application client to compare. Only user data is compared within each logical block.		
	No	No protection information or the medium or received from application client to compare. Only user data is compared within each logical block.		
001b ^b	Yes	LOGICAL BLOCK GUARD	Shall	LOGICAL BLOCK GUARD CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG (ATO = 1) ^e	Shall	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG (ATO = 0) ^f	Shall not	No compare performed
		LOGICAL BLOCK REFERENCE TAG (not type 3)	Shall	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
		<u>LOGICAL BLOCK REFERENCE TAG (type 3 and ATO = 0)</u>	Shall	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
		<u>LOGICAL BLOCK REFERENCE TAG (type 3 and ATO = 1)</u>	Shall not	No compare performed
	No	Error condition ^a		
010b ^b	Yes	LOGICAL BLOCK GUARD	Shall not	No compare performed
		LOGICAL BLOCK APPLICATION TAG (ATO = 1) ^e	Shall	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG (ATO = 0) ^f	Shall not	No compare performed
		LOGICAL BLOCK REFERENCE TAG (not type 3)	Shall	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
		<u>LOGICAL BLOCK REFERENCE TAG (type 3 and ATO = 0)</u>	Shall	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
		<u>LOGICAL BLOCK REFERENCE TAG (type 3 and ATO = 1)</u>	Shall not	No compare performed
	No	Error condition ^a		

Table 11 — VRPROTECT field with BYTCHK set to one - byte-by-byte comparison requirements (part 2 of 2)

Code	Logical unit formatted with protection information	Field	Byte-by-byte Comparison	If compare fails ^{c d} , additional sense code
011b 100b ^b	Yes	LOGICAL BLOCK GUARD	Shall	LOGICAL BLOCK GUARD CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG (ATO = 1) ^e	Shall	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG (ATO = 0) ^f	Shall not	No compare performed
		LOGICAL BLOCK REFERENCE TAG (not type 3)	Shall	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
		LOGICAL BLOCK REFERENCE TAG (type 3 and ATO = 0)	Shall	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
		LOGICAL BLOCK REFERENCE TAG (type 3 and ATO = 1)	Shall not	No compare performed
	No	Error condition ^a		
101b ^b	Yes	LOGICAL BLOCK GUARD	Shall	LOGICAL BLOCK GUARD CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG (ATO = 1) ^e	Shall	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG (ATO = 0) ^f	Shall not	No compare performed
		LOGICAL BLOCK REFERENCE TAG	Shall not	No compare performed
	No	Error condition ^a		
110b - 111b	Reserved			
^a A verify operation to a logical unit that supports protection information (see 4.17) and has not been formatted with protection information shall be terminated with CHECK CONDITION status with the sense key set to ILLEGAL REQUEST and the additional sense code set to INVALID FIELD IN CDB. ^b If the logical unit does not support protection information the requested command should be terminated with CHECK CONDITION status with the sense key set to ILLEGAL REQUEST and the additional sense code set to INVALID FIELD IN CDB. ^c If an error is reported, the sense key shall be set to MISCOMPARE. ^d If multiple errors occur, the selection of which error to report is not defined by this standard. ^e If the ATO bit is set to one in the Control mode page (see SPC-4), the logical block application tag shall not be modified by a device server. ^f If the ATO bit is set to zero in the Control mode page (see SPC-4), the logical block application tag may be modified by a device server.				

2.5 WRITE (10) command

....

Table 12 — WRPROTECT field (part 1 of 2)

Code	Logical unit formatted with protection information	Field in protection information	Device server check	If check fails ^{d i} , additional sense code
000b	Yes ^{f g h}	No protection information received from application client to check		
	No	No protection information received from application client to check		
001b ^b	Yes ^e	LOGICAL BLOCK GUARD	Shall	LOGICAL BLOCK GUARD CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG	May ^c	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
		LOGICAL BLOCK REFERENCE TAG	Shall (except for type 3) ^j	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
	No ^a	No protection information available to check		
010b ^b	Yes ^e	LOGICAL BLOCK GUARD	Shall not	No check performed
		LOGICAL BLOCK APPLICATION TAG	May ^c	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
		LOGICAL BLOCK REFERENCE TAG	May ^j	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
	No ^a	No protection information available to check		
011b ^b	Yes ^e	LOGICAL BLOCK GUARD	Shall not	No check performed
		LOGICAL BLOCK APPLICATION TAG	Shall not	No check performed
		LOGICAL BLOCK REFERENCE TAG	Shall not	No check performed
	No ^a	No protection information available to check		
100b ^b	Yes ^e	LOGICAL BLOCK GUARD	Shall	LOGICAL BLOCK GUARD CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG	Shall not	No check performed
		LOGICAL BLOCK REFERENCE TAG	Shall not	No check performed
	No ^a	No protection information available to check		
101b ^b	Yes ^e	LOGICAL BLOCK GUARD	Shall	LOGICAL BLOCK GUARD CHECK FAILED
		LOGICAL BLOCK APPLICATION TAG	May ^c	LOGICAL BLOCK APPLICATION TAG CHECK FAILED
		LOGICAL BLOCK REFERENCE TAG	May ^j	LOGICAL BLOCK REFERENCE TAG CHECK FAILED
	No ^a	No protection information available to check		
110b - 111b	Reserved			

Table 12 — WRPROTECT field (part 2 of 2)

Code	Logical unit formatted with protection information	Field in protection information	Device server check	If check fails ^{d i} , additional sense code
a	A write operation to a logical unit that supports protection information (see 4.17) and has not been formatted with protection information shall be terminated with CHECK CONDITION status with the sense key set to ILLEGAL REQUEST and the additional sense code set to INVALID FIELD IN CDB.			
b	If the logical unit does not support protection information the requested command should be terminated with CHECK CONDITION status with the sense key set to ILLEGAL REQUEST and the additional sense code set to INVALID FIELD IN CDB.			
c	The device server may check the logical block application tag if the ATO bit is set to one in the Control mode page (see SPC-4) and if it has knowledge of the contents of the LOGICAL BLOCK APPLICATION TAG field. If the WRITE (32) command (see 5.30) is used, this knowledge is obtained from the EXPECTED LOGICAL BLOCK APPLICATION TAG field and the LOGICAL BLOCK APPLICATION TAG MASK field in the CDB. Otherwise, this knowledge is obtained by a method not defined by this standard.			
d	If an error is reported, the sense key shall be set to ABORTED COMMAND.			
e	Device server shall preserve the contents of protection information (e.g., write to medium, store in non-volatile memory).			
f	The device server shall write a properly generated CRC (see 4.17.4.2) into each LOGICAL BLOCK GUARD field.			
g	If the P_TYPE field is set to 000h in the READ CAPACITY (16) parameter data (see 5.13), the device server shall write the least significant four bytes of each LBA into the LOGICAL BLOCK REFERENCE TAG field of each of the written logical blocks. If the P_TYPE field is not set to 000b, the device server shall write a value of FFFFFFFFh into the LOGICAL BLOCK REFERENCE TAG field of each of the written logical blocks.			
h	If the ATO bit is set to one in the Control mode page (see SPC-4), the device server shall write FFFFh into each LOGICAL BLOCK APPLICATION TAG field. If the ATO bit is set to zero, the device server may write any value into each LOGICAL BLOCK APPLICATION TAG field.			
i	If multiple errors occur, the selection of which error to report is not defined by this standard.			
j	If type 1 protection is enabled, the device server checks the logical block reference tag by comparing it to the lower 4 bytes of the LBA associated with the logical block. If type 2 protection or type 3 protection is enabled <u>and the device server has knowledge of the contents of the LOGICAL BLOCK REFERENCE TAG field, then</u> the device server checks the logical block reference tag if it has knowledge of the contents of the LOGICAL BLOCK REFERENCE TAG field . If type 2 protection is enabled, then this knowledge may be acquired through the EXPECTED INITIAL LOGICAL BLOCK REFERENCE TAG field in a WRITE (32) command (see 5.30). <u>If type 3 protection is enabled, the ATO bit is set to one in the Control mode page (see SPC-4), and the device server has knowledge of the contents of the LOGICAL BLOCK REFERENCE TAG field, then the device server may check the logical block reference tag.</u> If type 3 protection is enabled, then the method for acquiring this knowledge is not defined by this standard.			

2.6 WRITE (6) command

...

If a WRITE (6) command is received after protection information is enabled the device server shall set the protection information (see 4.17) as follows as it writes each logical block to the medium:

- a) the LOGICAL BLOCK GUARD field set to a properly generated CRC (see 4.17.4);
- b) the LOGICAL BLOCK REFERENCE TAG field set to:
 - A) the least significant four bytes of the LBA, if type 1 protection (see 4.17.2.3) is enabled; ~~or~~
 - B) FFFFFFFFh, if type 2 protection (see 4.17.2.4) ~~is~~ enabled;
 - C) FFFFFFFh, if the ATO bit is set to one in the Control mode page (see SPC-4) and type 3 protection (see 4.17.2.5) is enabled; or
 - D) any value, if the ATO bit is set to zero in the Control mode page (see SPC-4) and type 3 protection (see 4.17.2.5) is enabled;

and

- c) the LOGICAL BLOCK APPLICATION TAG field set to:
 - A) FFFFh, if the ATO bit is set to one in the Control mode page (see SPC-4); or
 - B) any value, if the ATO bit is set to zero in the Control mode page (see SPC-4).

2.7 WRITE SAME (10) command

...

Table 13 — LBADATA bit and PBADATA bit

LBADATA	PBADATA	Description
0	0	<p>The device server shall write the single block of user data received from the data-out buffer to each logical block without modification.</p> <p>If the medium is formatted with type 1 or type 2 protection information:</p> <ul style="list-style-type: none"> a) the value in the LOGICAL BLOCK REFERENCE TAG field received in the single block of data from the data-out buffer shall be placed into the LOGICAL BLOCK REFERENCE TAG field of the first logical block written to the medium. Into each of the subsequent logical blocks, the device server shall place into the LOGICAL BLOCK REFERENCE TAG field the value of the previous logical block's LOGICAL BLOCK REFERENCE TAG field plus one; b) If the ATO bit is set to one in the Control mode page (see SPC-4), the logical block application tag received in the single block of data shall be placed in the LOGICAL BLOCK APPLICATION TAG field of each logical block. If the ATO bit is set to zero, the device server may write any value into the LOGICAL BLOCK APPLICATION TAG field of each logical block; and c) The value in the LOGICAL BLOCK GUARD field received in the single block of data from the data-out buffer shall be placed in the LOGICAL BLOCK GUARD field of each logical block. <p><u>If the medium is formatted with type 3 protection information:</u></p> <ul style="list-style-type: none"> a) <u>If the ATO bit is set to one in the Control mode page (see SPC-4), then the logical block reference tag received in the single block of data shall be placed in the LOGICAL BLOCK REFERENCE TAG field of each logical block. If the ATO bit is set to zero, then the device server may write any value into the LOGICAL BLOCK REFERENCE TAG field of each logical block;</u> b) <u>If the ATO bit is set to one in the Control mode page (see SPC-4), then the logical block application tag received in the single block of data shall be placed in the LOGICAL BLOCK APPLICATION TAG field of each logical block. If the ATO bit is set to zero, then the device server may write any value into the LOGICAL BLOCK APPLICATION TAG field of each logical block; and</u> c) <u>The value in the LOGICAL BLOCK GUARD field received in the single block of data from the data-out buffer shall be placed in the LOGICAL BLOCK GUARD field of each logical block.</u>
0	1 ^a	<p>The device server shall replace the first eight bytes of the block received from the data-out buffer to each physical sector with the physical address of the sector being written using the physical sector format (see 5.2.2.4.5).</p>
<p>^a If the medium is formatted with protection information then the protection information shall be written to a default value of FFFFFFFF_FFFFFFFFh in each of the written logical blocks.</p>		

Table 13 — LBADATA bit and PBDATA bit

LBADATA	PBDATA	Description
1 ^a	0	The device server shall replace the first four bytes of the block received from the data-out buffer with the least significant four bytes of the LBA of the block being written, ending with the least significant byte (e.g., if the LBA is 77665544_33221100h, 33221100h is written with 33h written first and 00h written last).
1	1	The device server shall terminate the command with CHECK CONDITION status with the sense key set to ILLEGAL REQUEST and the additional sense code set to INVALID FIELD IN CDB.
^a If the medium is formatted with protection information then the protection information shall be written to a default value of FFFFFFFF_FFFFFFFFh in each of the written logical blocks.		

3 SPC-4 changes

7.4.6 Control mode page

....

~~An application tag owner (ATO) bit set to one specifies that the contents of the LOGICAL BLOCK APPLICATION TAG field in the protection information (see SBC-2), if any, shall not be modified by the device server. An ATO bit set to zero specifies that the contents of the LOGICAL BLOCK APPLICATION TAG field in the protection information, if any, may be modified by the device server. If the ATO bit is set to zero, the device server shall ignore the contents of the LOGICAL BLOCK APPLICATION TAG field in the protection information when received from the application client.~~

If the ATO bit is set to zero the device server may modify the contents of the LOGICAL BLOCK APPLICATION TAG field and, depending on the protection type, may modify the contents of the LOGICAL BLOCK REFERENCE TAG field (see SBC-3). If the ATO bit is set to one the device server shall not modify the LOGICAL BLOCK APPLICATION TAG field and, depending on the protection type, shall not modify the contents of the LOGICAL BLOCK REFERENCE TAG field (see SBC-3)