

To: X3T10 Committee (SCSI)

From: George Penokie (IBM)

Subject: Logical unit response to transceiver change

## 1 Introduction

The following proposal describes additions to SAM-2, SPC-2, and SPI-2 (old SIP clauses) that are required to cause a unit attention condition to occur as a result of a target being forced to switch from LVD transceivers to SE transceivers. This event would occur when a single ended device is plugged into a bus that only has low voltage differential devices and would only apply to LVD devices that support multi-mode operations.

## 2 SAM-2 changes

In the Unit Attention Condition clause the following would be added to the unit attention condition events list:

x) A change in the transceiver mode from low voltage differential mode to single ended mode.

## 3 SPC-2 changes

The following ASC and ASCQ would be added:

xx 00 all devices TRANSCEIVER MODE CHANGE

xx 01 all devices TRANSCEIVER MODE CHANGED TO SE

xx 02 all devices TRANSCEIVER MODE CHANGED TO LDV

## 4 SPI-2 changes (SPI-2 clauses from SIP)

### 4.1 SDTR message description

Add to the list of conditions that cause the SDTR agreement to become invalid the following:

e) A change in the transceiver mode from low voltage differential mode to single ended mode.

### 4.2 WDTR message description

Add to the list of conditions that cause the WDTR agreement to become invalid the following:

d) A change in the transceiver mode from low voltage differential mode to single ended mode.

### 4.3 Command processing considerations and exception conditions clause

Add a subclause to the Command processing considerations and exception conditions clause titled 'Transceiver mode change' as follows:

When a target role agent that contains multimode transceivers detects a transceiver mode change from low voltage differential mode to single ended mode it shall create a unit attention condition for all initiators. The unit attention condition sense key shall be set to UNIT ATTENTION, and the additional sense code set to LVD TRANSCEIVER CHANGE TO SE.