

**TO:** T10 Membership  
**FROM:** Paul A. Suhler, Quantum Corporation  
**DATE:** 5 May 2008  
**SUBJECT:** T10/08-226r0, ADC-3: Add Port and Node Name to Fibre Channel Port Status Data

**1 Revisions**

0 Initial revision (5 May 2008)

Unless otherwise indicated additions are shown in blue, deletions in red-strikethrough, and comments in green.

**2 General**

ADC-2 letter ballot comment HPQ-206 requested adding the Port\_Name and Node\_Name to the Fibre Channel Port status data in the DT device primary port status log parameter.

**3 Changes**

**3.1 Changes to clause 6.1.2.6.2**

3.1.1 Change to Table 27:

Bit	7	6	5	4	3	2	1	0
0	CURRTOP	CURRENT SPEED			LC	CONFLICT	SIGNAL	PIC
1	(MSB)	CURRENT N_PORT_ID						
3		(LSB)						
4		Reserved						
6		Reserved						
7	Reserved	CURRENT FC-AL LOOP ID						
8		CURRENT PORT NAME						
11		CURRENT PORT NAME						
12		CURRENT NODE NAME						
15		CURRENT NODE NAME						

Add the following two paragraphs at the end of clause 6.1.2.6.2:

The CURRENT PORT NAME field contains the DT device's primary port name identifier (see FC-FS).

The CURRENT NODE NAME field contains the DT device's primary node name identifier (see FC-FS).